

SCIENTIFIC AMERICAN

[Entered at the Post Office of New York, N. Y., as Second Class matter. Copyright, 1895, by Munn & Co.]

A WEEKLY JOURNAL OF PRACTICAL INFORMATION, ART, SCIENCE, MECHANICS, CHEMISTRY, AND MANUFACTURES.

Vol. LXXII.—No. 26.
ESTABLISHED 1845.

NEW YORK, JUNE 29, 1895

[\$3.00 A YEAR.
WEEKLY.]


ELECTRICALLY OPERATED WATER SUPPLY PLANT, DE KALB, ILL.

For the water supply of De Kalb, Ill., a city of 3,000 inhabitants, the water has, until recently, been raised from a well close to a stand pipe, by means of steam pumps, requiring the usual services of an engineer and attendant. When an electric system of lighting was inaugurated in the city, a proposition was accepted by the authorities to have the pumps run by the surplus current from the electric plant, and this system was completed and put in operation in February last. Our illustrations, sketched from the works, show the manner in which this is ac-

and motors are shown in the large general interior of the new pump house.

The water is raised from a well which is 900 feet deep, the water level being 65 feet from the surface of the ground, by a motor and lift pump, to a small supply reservoir just outside the pump house; from this reservoir it is taken by two large size Gould triplex pumps, and forced to the mains and stand pipe, the latter being 18 feet in diameter, power being obtained from electric motors of high running speed, and geared down, as clearly shown in our view.

The electrical plant is supplied with one double, upright direct-attached 150 horse power 50 kilowatt engine and dynamo, shown in lower small view, and two horizontal belt engines and dynamos, 100 horse power



THE DE KALB, ILL., ELECTRIC PUMPS.

complished. The smaller view at the top shows the former steam pump, boiler, coal house, and stand pipe. One of the dynamos in use at the electric plant fills the lower smaller view, while the Gould triplex pumps

combined, 25 kilowatt. The Edison three-wire system is used, and the connection to the pump house is over a 0000 copper conductor.

The requirements were for a constant level of water

of 85 feet in the stand pipe, with an increased pressure in the mains in an emergency of fire, the increase of pressure being obtained by use of an automatic closing valve at the stand pipe, when a fire pressure was required. An ordinary pressure of 40 pounds is maintained in the mains for domestic service, and in case of fire the pressure is raised to 125 pounds.

The pump house shown is fully one-half mile from the electric plant, and the pumps are controlled entirely by means of a switch at the electric power house. The system has been found to meet all the requirements.

Corn Stalks and Coconut Husks.

In view of the great rapidity with which the modern rapid-fire guns can deliver shells, it has been felt for some time that, in addition to watertight subdivisions in war ships, other means of preventing any inflow of water should be used. The most favored method of accomplishing this result has been to fit a coffer dam, or double skin, for some distance above and below the water line, the space between being about three feet thick and filled with material which would expand and keep out water when a shot passed through. The material that was adopted in the United States navy for this purpose in 1892, called cellulose, is obtained from the husks of coconuts, being a brown, powdery substance, very light, and admitting of a good deal of compression. It was first used in France, and has been more or less used by various other foreign nations.

A Philadelphia inventor has recently brought to the attention of the Navy Department a new cellulose, composed of the pith of cornstalks, which is granulated by machinery. Secretary Herbert has determined to thoroughly investigate the new substance, and a board of experts was appointed a few weeks ago to conduct experiments. This board had duplicate coffer dams constructed, measuring six feet square and three feet thick, one packed with cocoa fiber and the other with cornstalk cellulose. A six and an eight inch shell were fired into each. Water was then forced into the dams under pressure. The water failed to penetrate the Marsden or American cellulose dam, but oozed through the cocoa product in a short time.

The English battle ship Inflexible is protected by coffer dams filled with a mixture of cork and oakum, which aggregates in weight 143 tons. With the French cocoa cellulose this weight would be reduced to 43 tons, while the American corn product would not weigh over 25 tons and furnish, it is claimed, more reliable protection.

Photography in Natural Colors.

A. and L. Lumiere point out that the indirect method of photographing in natural colors has not received a proper practical application, because of the difficulty experienced in selecting the colors and in preparing and superposing the monochromes. They recommend the use of orange, green and violet screens for preparing three series of negatives presenting a maximum of sensibility to the rays which the respective screens allow to pass. Specimens of photographs so prepared were exhibited before the Paris Academy of Sciences. The printing and superposition of the monochromes have been successfully accomplished by employing bichromated gelatine to which are added substances insoluble under certain conditions. If, for example, 5 per cent of ammonium bichromate and 5 to 10 per cent of silver bromide in the form of emulsion be added to a 10 per cent solution of gelatine, and the preparation be spread in a thin layer upon a plate of glass, a surface is obtained which can be exposed under a negative and will reproduce the picture by the action of light. After exposure the plate is washed with cold water, and the portion of the film acted upon by light, being rendered insoluble, remains and serves to print the image from on the application of suitable colors. The silver bromide, which, by the way, may be replaced by other insoluble precipitates, is easily removed by the action of sodium hyposulphite, and proofs can then be printed from the plate in any color, showing all the gradations of tint present in the negative. Polychrome prints may be obtained by receiving on the same plate monochrome red, yellow and blue images successively, by means of three corresponding negatives, and isolating each image from the preceding one by an impervious layer of collodion. By employing dyes of greater or less concentration or by simple decoloration with water, variation in the relative intensity of the monochromes is readily obtained.—Comp. Rend.

THE proprietors of the New York Recorder recently offered a prize for a relay bicycle race from Chicago to New York, distance by road about 1,000 miles. The race was finished on the 8th inst., time 64 hours 57 minutes and 30 seconds. A crowd of 10,000 persons gathered at the Metropolitan Bicycle Academy, corner 60th Street and Boulevard, New York, to witness the coming in of the two riders, the red and the blue. The finish took place at 1:57 A. M., when the red rider came in about an hour ahead of the blue.

Scientific American.

ESTABLISHED 1845.

MUNN & CO., Editors and Proprietors.

PUBLISHED WEEKLY AT

No. 361 BROADWAY, NEW YORK.

O. D. MUNN.

A. E. BEACH.

TERMS FOR THE SCIENTIFIC AMERICAN.

One copy, one year, for the U. S., Canada or Mexico.....\$3 00
One copy, six months, for the U. S., Canada or Mexico..... 1 50
One copy, one year, to any foreign country belonging to Postal Union. 4 00
Remit by postal or express money order, or by bank draft or check.
MUNN & CO., 361 Broadway, corner of Franklin Street, New York.

The Scientific American Supplement

is a distinct paper from the SCIENTIFIC AMERICAN. THE SUPPLEMENT is issued weekly. Every number contains 16 octavo pages, uniform in size with SCIENTIFIC AMERICAN. Terms of subscription for SUPPLEMENT, \$5.00 a year, for the U. S., Canada or Mexico. \$6.00 a year to foreign countries belonging to the Postal Union. Single copies 10 cents. Sold by all newsdealers throughout the country. See prospectus, last page.
Combined Rates.—The SCIENTIFIC AMERICAN and SUPPLEMENT will be sent for one year, to one address in U. S., Canada or Mexico, on receipt of seven dollars. To foreign countries within Postal Union eight dollars and fifty cents a year.

Building Edition of Scientific American.

THE BUILDING EDITION OF THE SCIENTIFIC AMERICAN is a large and splendidly illustrated periodical, issued monthly, containing floor plans and perspective views pertaining to modern architecture. Each number is illustrated with beautiful plates, showing desirable dwellings, public buildings and architectural work in great variety. To builders and all who contemplate building this work is invaluable. Has the largest circulation of any architectural publication in the world.
Single copies 25 cents. By mail, to any part of the United States, Canada or Mexico, \$2.50 a year. To foreign Postal Union countries, \$3.00 a year. Combined rate for BUILDING EDITION with SCIENTIFIC AMERICAN, to one address, \$5.00 a year. To foreign Postal Union countries, \$6.50 a year. Combined rate for BUILDING EDITION, SCIENTIFIC AMERICAN and SUPPLEMENT, \$9.00 a year. To foreign Postal Union countries, \$11.00 a year.

Export Edition of the Scientific American.

with which is incorporated "LA AMERICA CIENTIFICA E INDUSTRIAL," or Spanish edition of the SCIENTIFIC AMERICAN, published monthly, uniform in size and typography with the SCIENTIFIC AMERICAN. Every number contains 16 pages, profusely illustrated with beautiful plates of scientific, industrial, export paper published. It circulates throughout Cuba, the West Indies, Mexico, Central and South America, Spain and Spanish possessions—wherever the Spanish language is spoken. THE SCIENTIFIC AMERICAN EXPORT EDITION has a large guaranteed circulation in all commercial places throughout the world. \$3.00 a year, post paid to any part of the world. Single copies 25 cents.

Manufacturers and others who desire to secure foreign trade, may have large and handsomely displayed announcements published in this edition at a very moderate cost. MUNN & CO., Publishers, 361 Broadway, New York.

The safest way to remit is by postal order, express money order, draft or bank check. Make all remittances payable to order of MUNN & CO.

Readers are specially requested to notify the publishers in case of any failure, delay, or irregularity in receipt of papers.

NEW YORK, SATURDAY, JUNE 29, 1895.

Contents.

(Illustrated articles are marked with an asterisk.)

Ash sifter, Briner's.....	404	Inventions, recently patented.....	411
Artesian well, oil, gas, and water from.....	407	Kiel Canal celebration, the, in Germany.....	402
Bicycle's distance recorder.....	405	Lakes, temperature of.....	402
Bicycle, the.....	409	Lead wort, the.....	404
Bonaparte and the ratchet meter.....	403	Lens, the great Yerkes, testing.....	403
Books and publications, new.....	411	Life, long, secret of.....	403
Botanical garden, the New York.....	405	Loading an ocean steamer.....	410
Brake slack adjuster, Freese & Nicholson's.....	405	Lubrication, uneconomical.....	411
Bursting of a cream separator.....	409	Notes and queries.....	403
Cable, Atlantic, projectors of the.....	408	Odometer, the Bell.....	405
Canal, Harlem, opening.....	409	Organ of steamer St. Louis.....	408
Canal, ship, Block Island.....	402	Patent decisions of the courts.....	403
Cellulose for skins of vessels.....	402	Patents granted, weekly record.....	412
Cleaning House, N. Y. vault.....	411	Photography in natural colors.....	410
Clothes wringer (5560).....	411	Piano action frame, Bothmer's.....	404
Cotton crop, the, of 1895.....	407	Flow, faults of the.....	410
Electrically operated pumps.....	401	Powder, cost of, at sea.....	403
Electrical notes.....	407	Rifle, the Blake repeating.....	406
Franklin, Benjamin, on torpedo.....	407	Steam trap, the Bundy.....	406
French infantry.....	403	Street car fenders.....	406
Glass, silvering.....	403	Sweeper, street car, Walte's.....	404
Hair curler, Brand's.....	404	Tanning, quebracho for.....	404
Ignorance not a legal defense.....	403	Water supply, DeKalb, Ill.....	407
Insects and flowers.....	410	Welding, electric.....	407
		Wheel, the, how to ride.....	406
		Yellowstone Park falls and geysers.....	408

TABLE OF CONTENTS OF SCIENTIFIC AMERICAN SUPPLEMENT No. 1017.

For the Week Ending June 29, 1895.

Price 10 cents. For sale by all newsdealers.

I. CHEMISTRY.—Detection of Blood Spots in Presence of Rust.—By Herren MECKE and WIMMER.—An important contribution to the literature of medical jurisprudence.....	16258
II. CIVIL ENGINEERING.—The Boston Electric Railway Subway, description of this important engineering work which will extend from the Fitchburg Railway Station to the Public Garden, and will relieve the streets of this congested district.—With profiles and cross sections of the subway.—The total cost of the improvement will be about \$5,000,000.—The article includes a map and view of one of the stations.—10 illustrations.....	16254
III. CIVIL ENGINEERING.—The Chicago Drainage Canal.—A description of this great engineering work, from its inception to the present time.—The estimated cost of this work is \$21,798,203.—It will be completed about November 1, 1896.—The article gives illustrations of graders, derricks, cantilevers, and hoisting machinery.—9 illustrations.—The Effects of the canal on the Commerce of the Lakes.—This article includes the estimates of the amount that the canal will probably lower the lake level and the damage that would result thereby to the commerce of the lakes.....	16248
IV. ELECTRICITY.—The Iodine Voltmeter.—A full description of the new delicate form of voltmeter, which is especially valuable for weak currents.....	16253
V. MECHANICAL ENGINEERING.—The Old and the New.—By ROBERT ALLISON.—A paper presented at the Detroit meeting (June, 1895) of the American Society of Mechanical Engineers.—Includes a discussion by Mr. Samuel Webber and others, containing many reminiscences of old tools and methods of practice..... Rustless Coatings for Iron and Steel.—Paints.—Of what composed, how destroyed, classification as true pigments and inert substances, adulterants, etc.—By P. M. WOOD.—An important paper, giving the results of many experiments on the protection of iron and steel, including natural and artificial asphalt coatings.....	16238
V. METALLURGY.—The Rarer Metals and Their Alloys.—Continuation of Professor Roberts-Austen's valuable lecture read at the Royal Institution.—The subject of the subject of armor plates and attack of projectiles, and the preparation for the microscope of diamonds and other forms of carbon obtained from carbonized iron.—5 illustrations.....	16256
VI. MINERALOGY.—Corundum Deposits of Georgia.....	16258
VII. NATURAL HISTORY.—The Action of Light on Animal Life.—The present article discusses the question of whether sunshine increases or diminishes an animal's susceptibility to disease.....	16258
VIII. PHOTOGRAPHY.—Binocular Photomicrography.—By Hon. A. A. DEE.—Contains the result of a series of interesting experiments.....	16255
IX. PHYSICS.—Breath Figures.—By Dr. J. G. McPHERSON, F.R.S.E.—Interesting paper on this curious phenomenon.—Gives a number of examples.—No one, as yet, has clearly explained how these impressions are produced by heat and electricity.....	16253

THE CELEBRATION IN GERMANY.

The ship canal recently opened across the northern peninsula of Germany was celebrated with rejoicings and festivities by the people of that great empire. On the invitation of the Emperor the representatives of the leading foreign governments took part; England, France, Russia and Italy sent some of their greatest war ships. The naval pageant was very grand. It is gratifying to know that the United States was represented by four such noble vessels as the Columbia, the New York, the San Francisco and the Marblehead. Report says the American ships presented a more attractive appearance and excited more interest than any of the assembled fleets, due, no doubt, to the white color of our ships, their clean and graceful lines.

The new canal, while it is a work of high importance to Germany as a means of defense in time of war, and of special commercial advantage in time of peace to her, to England and other nations of Northern Europe, is likely to be of little utility for ships of the United States. Seldom, probably, will American vessels have occasion to use the canal. Yet a stranger might have supposed, from the ringing cheers and enthusiastic demonstrations of the populace, as the Marblehead came into view and passed from town to town, bearing the star spangled banner through the windings of the canal, that Germany considered the Americans as holding the greatest interests, next to themselves, in the success and operations of the new waterway. Doubtless it was the presence of the glorious old flag, the symbol of free institutions, under which so many Germans, so many of their own kindred, live and prosper, under which so many of them have fought and died, that roused their feelings and caused their acclamations. Next to the emblem of the Fatherland, no ensign is so dear to the German heart as the flag of the American Union.

TEMPERATURES OF LAKES.

Mr. Desmond Fitz Gerald, at the annual meeting of the American Society of Civil Engineers at Nantasket, June 18 to 22, read an interesting paper on the temperature of lakes, based on experiments made by him during the past five years. The author deduced from his observations that in lakes and ponds less than 25 feet in depth the temperature at the bottom does not differ materially from that at the surface. In deeper bodies of water, however, the conditions are quite different. Experiments made on Lake Cochituate, the base of the Boston water supply, showed that when the surface is frozen during the winter the temperature at the bottom is usually 39.2 degrees. The strata of water lie in the order of their densities, and the temperature decreases gradually until within a few feet of the surface, when it suddenly falls to a point just above freezing. The disposition of the strata is not disturbed after the forming of the ice until the spring thaws. By April 1, the surface water has become warmed to the same temperature as that at the bottom, and, as the whole body is in more or less unstable equilibrium, the winds and currents are sufficient to produce circulation from top to bottom. This continues until the first of May, when the surface temperature has risen about five degrees above that of the bottom. The consequent difference in density prevents further circulation, and, while the warming of the surface continues, the temperature of the bottom remains stationary until the middle of November.

During this period the summer stagnation takes place. The lower layers of the water gradually collect all the organic matter from the upper layers, and decay continues until there is no more oxygen left to support it. At the same time the water grows darker and more impure until by October it is usually offensive to the smell and has a dull yellow color. About November 1 the temperature of the bottom begins to rise, until by the middle of the month it has increased from 20° to 30°, at which point it equals that of the surface.

The temperature of the whole mass then falls at nearly the same rate during a second period of circulation until the surface freezes and stratification again takes place. During the November circulation, and again in the spring to a less extent, all the impure water at the bottom is brought to the surface and the infusoria and diatoms spring into life in great numbers, owing to the union of the organic matter from the bottom with the oxygen in the surface water.

Block Island Ship Canal and Harbor.

The new canal connecting Great Salt Pond, on Block Island, with the ocean, has been practically completed by the Hartford Dredging Company. The canal makes an entrance with one of the finest land-locked harbors along the Atlantic coast. The width is 400 feet and the depth 14 feet. The distance excavated from water to water is 600 feet. Inside the lake the excavation extends 200 feet, and outside the ocean entrance has been deepened for 400 feet, making a total of 1,200 feet. The breakwater is 600 feet long. This year \$50,000 has been appropriated for the work, and last year \$25,000.

Napoleon Bonaparte in Egypt and the Differential Refractometer at the Stevens Institute of Technology.

BY PRESIDENT HENRY MORTON, PH.D.

Now that so much is being said and published about Napoleon Bonaparte, it may interest our readers to know that in the physical cabinet of the Stevens Institute of Technology there is preserved a large piece of apparatus, the history of which, leading to its location as above, connects it with the grand though disastrous campaign in Egypt.

When Napoleon made his movement into Egypt he was accompanied by a number of prominent savants, members of the French Academy, who proceeded soon after their arrival to establish the French Academy of Egypt.

The most remarkable monument of their labors is found in the great work on Egypt, published by the French government, consisting of ten "elephant folios" of plates representing architectural monuments and inscriptions, as well as drawings of the fauna and flora of the country, and also comprising nine large octavo volumes of text.

At the same time they made arrangements for the pursuit of the higher lines of physical research, and for this purpose, among other things, ordered from the then famous instrument maker of Paris, J. Soleil, a piece of apparatus just devised by M. Arago, and called a differential refractometer.

However, before this apparatus was finished, Lord Nelson and the battle of Trafalgar intervened, and the address of the "French Academy of Egypt" became too uncertain to encourage the constructor in any attempt to deliver the instrument to those who had ordered it.

Under these circumstances, he looked around for another customer, and was glad to ship this apparatus—the largest of its kind ever built—to Mr. Charles Banker, of Philadelphia, who for many years had made it his pleasure to collect all sorts of philosophical apparatus, especially such as was unique and of special interest and value.

Mr. Banker had made during a long life, previous to 1870, a remarkable collection, filling several floors of a large dwelling house, and to this collection the present writer, for some years prior to that time, had almost exclusive access.

Mr. Banker died in 1870, without making any provision for keeping together his collection, and his executors offered it for sale. As the Stevens Institute of Technology was at that time about to begin its career, the present writer secured from the Banker collection all the most desirable objects, and among others this differential refractometer, whose original destination was Egypt.

Aside from these incidents of its early history, this apparatus is a remarkable one. It consists in the first place of a large and delicately adjustable vertical slot, through which light from the sun or other source may pass in a broad but thin vertical band or ribbon. This is received on a corrected lens which collimates or brings all rays into parallel lines, and then continues in two parallel portions, one traversing a closed tube having flat glass ends while the other passes beside it through the free air, but being obliged likewise to pass through glass plates identical with those closing the ends of the tube.

This portion is about a yard in length. The two parallel portions of the light then pass each through a narrow vertical slit and then through adjustable plates of parallel glass and enter the object glass of a large telescope, through the eye piece of which they are viewed.

If the conditions to which each half of the divided ray is subjected are identical, a series of what are called diffraction bands will appear in certain well known positions; but if the conditions are varied, as, for example, by substituting some other gas for air in the closed tube, or by changing the density of the air in this tube, these bands will be seen to shift to the right or left and more or less according to the character and degree of the changes made.

These shiftings may be corrected by adjustment of the two plates of glass, the effect of whose refraction will vary with their inclinations to the rays, and the law of this action being known, the effect of the changes in nature or in density of the gas or air in the inclosed tube upon the velocity of light may be calculated.

So sensitive is this action that if a long rubber tube is connected with the opening into the brass tube and closed at its extremity, the minute change in density of the inclosed air produced by pinching the tube in one place will cause the bands of interference to move sideways the width of one band, and if the open end of the rubber tube is held opposite to and near the mouth while speaking, the bands will be seen to flutter by reason of the changes in density developed in the air by the act of speaking.

A USE for compressed air in the foundry in addition to cranes and hoists, which are being introduced everywhere, is in providing a sand blast for the cleaning of castings.

DECISIONS RELATING TO PATENTS. Supreme Court of the United States.

EBY VS. KING ET AL.

Mr. Justice Brown delivered the opinion of the court.

Appeal from the Circuit Court of the United States for the Northern District of Illinois.

This was a bill in equity to recover damages for the infringement of reissued letters patent No. 7,851, granted August 21, 1877, to the plaintiff Eby, for an improvement in cob carriers for corn shellers.

Reissued letters patent No. 7,851, granted August 21, 1877, to Henry H. Eby for an improvement in cob carriers for corn shellers, Held to be void.

Where a reissue was obtained for the purpose of broadening the claims of the original patent to cover that which is presumed to have been once abandoned to the public, Held that the reissue is void. (White vs. Dunbar, 37 O. G., 1002; 119 U. S., 47; Ives vs. Sargent, 38 O. G., 781; 119 U. S., 652; Dunham vs. Dennison Mfg. Co., 67 O. G., 1571; 154 U. S., 103.)

When a patent has been surrendered and a reissue obtained and such reissue is held to be void, the patentee cannot proceed upon his original patent. (Moffitt vs. Garr, 1 Black, 273; Reedy vs. Scott, 7 O. G., 463; 23 Wall., 352, 364; Peck vs. Collins, 19 O. G., 1137; 103 U. S., 660; McMurray vs. Mallory, 27 O. G., 915; 111 U. S., 97, referred to and reviewed.)

The Commissioner is authorized to reissue patents in certain specified cases, and if the petition makes no pretense of setting forth facts entitling the patentee to a reissue, it is exceedingly doubtful whether he obtains any jurisdiction under section 4,916 Revised Statutes, to act upon such petition.

Supreme Court of the United States.

RICHARDS VS. CHASE ELEVATOR COMPANY.

Appeal from the Circuit Court of the United States for the Northern District of Illinois.

This was a bill in equity for the infringement of letters patent No. 308,095, issued November 18, 1884, to the plaintiff Richards for a grain transferring apparatus.

The claims of letters patent No. 308,095, issued November 18, 1884, to Edward S. Richards for a grain transferring apparatus, Held to be for a pure aggregation of old elements.

So long as each element performs some old and well-known function the result is not a patentable combination, but an aggregation of elements. The multiplicity of elements may go on indefinitely without creating a patentable combination, unless by their collocation a new result be produced.

While patent cases are usually disposed of upon bill, answer, and proof, there is no objection, if the patent be manifestly invalid upon its face, to the point being raised on demurrer and the case being determined upon the issue so formed. The Supreme Court has repeatedly held that a patent may be declared invalid for want of novelty, though no such defense be set up in the answer. (Dunbar vs. Myers, 11 O. G., 35; 94 U. S., 187; Slawson vs. Grand Street RR. Co., 24 O. G., 99; 107 U. S., 649; Brown vs. Piper, 10 O. G., 417; 91 U. S., 37.)

U. S. Circuit Court—Northern District of Illinois. AMERICAN FIBER CHAMOIS COMPANY VS. DE LEE & DERNBERG.

Showalter, J.:

Trade Mark Valid.—The combined words "Fiber Chamois," as applied to a fabric used as an interlining for women's dresses, Held to have a significance as an arbitrary mark and name, whereby the goods made by complainant are identified and distinguished in the trade as carried on.

The Secret of Long Life.

M. Barthelmy Saint Hilaire, the famous French scholar and politician, who recently entered on his 90th year full of physical and intellectual vigor, has been telling the inevitable interviewer how it is his days have been so long in the land. It is, we are told, the effect of strict adherence to the old precept "early to bed and early to rise," with steady work during waking hours. Every grand old man seems to have a secret of his own. Mr. Gladstone, we believe, attributes his longevity to his habit of taking a daily walk in all weathers, and to his giving thirty-two bites to every morsel of food. Oliver Wendell Holmes pinned his faith on equability of temperature. The late Major Knox Holmes swore by the tricycle, which, in the end, was the cause of his death. Dr. P. H. Van der Weyde, an American octogenarian, not long ago offered himself "as an example of the benign influence of the study and practice of music." Some aged persons give the credit of their long lives to abstinence from tobacco, alcohol, meat, or what not; others to their indulgence in all these things. One old lady of whom we read not long ago as having reached the age of 120 or thereabout, maintained that single blessedness is the real elixir vitae, and she ascribed the death of a brother at the tender age of 90 to the fact that he had committed matrimony in early life. M. Ferdinand de Lesseps be-

lieved in horse riding. Mr. James Payn complains that in his boyhood he "got a little bored with too much horse." The Grand Français seemed to think that one can hardly have "too much horse." In a letter recently published, M. De Lesseps delivered himself on the subject as follows: "I shall always feel deeply grateful to Larine, my riding master, who from my earliest years made me share his keen passion for horses, and I am still convinced that daily horse exercise has in a large measure been the means of enabling me to reach my 84th year in perfect health." Carlyle was also a great rider almost to the end of his long life, and he not only rode, but, we believe, groomed his horse himself. On the whole, it must be concluded that the real secret of longevity is a sound constitution prudently husbanded. The only general rules that can be laid down are those set forth by Adam in "As You Like It":

Though I look old, yet I am strong and lusty;
For in my youth I never did apply
Hot and rebellious liquors in my blood,
Nor did not with unashful forehead woo
The means of weakness and debility;
Therefore my age is as a lusty winter,
Frosty but kindly.

That is the whole secret of long life. Shakespeare knew it as well as any one, yet he died at 52.—Br. Med. Jour.

Ignorance not a Valid Defense.

By a recent decision reported in the American Lawyer, a person who signs an instrument without reading it, when he can read, cannot, in the absence of fraud, deceit or misrepresentation, avoid the effect of his signature, because not informed of the contents of the instrument. The same rule would apply to one who cannot read, if he neglects to have it read, or to inquire as to its contents. This well settled rule is based upon the sufficient reason that in such cases ignorance of the contents of instruments is attributable to the party's own negligence. But the rule is otherwise where the execution of an instrument is obtained by a misrepresentation of its contents; where the party signed a paper he did not know he was signing, and did not really intend to sign. It is immaterial, in the latter aspect of the case, that the party signing had an opportunity to read the paper, for he may have been prevented from doing so by the very fact that he trusted to the truth of the representation made by the other party with whom he was dealing.

This is the clear-cut manner in which the Supreme Court of Alabama, in the case of Beck & Pauli Lithographing Co. v. Houppert et al. (16 So. Rep. 522), reiterates the wholesome doctrine that a person cannot take advantage of his own wrong or negligence.

Uneconomical Lubrication.

It is said that elaborate tests and investigations made a short time ago upon one of the largest railroads in the country showed that more than one-third of all the lubricating material supplied in a given time was wasted and lost by carelessness in handling, leakage, etc. A great deal of this waste oil is drawn from the journal boxes by the centrifugal force of the rapidly moving wheels and deposited upon the track. The ties and wooden bridges are injured and destroyed by being thus constantly soaked with oil, and are also rendered highly inflammable. These difficulties have led to the adoption of various kinds of solid or semi-solid grease in place of oil. A lubricant of this kind is now in use which seems to be all that could be wished, if the claims made for it are true. It is said that red hot iron will not burn it, water will not wash it off, steam at 90 pounds pressure will not remove it. It is used with cotton waste in ordinary journal boxes, and is said to be so tenacious that no amount of jarring will shake it from the fibers and allow it to leak out upon the wheels. Its lubricating power is claimed to be such that one package has sufficed for a run of 50,000 miles, representing more than a year of service.


Vault of the New York Clearing House.

The vault for the New York Clearing House is the strongest in the world. It weighs 571,400 pounds, is 24 feet 4 inches wide, 16 feet 10½ inches deep and 11 feet 6½ inches in height. It is divided into three equal compartments, access to which is given by six doors, three of them weighing 16,800 pounds each. The old method of construction in which a bank vault rests on a stone foundation to guard against tunneling has been abandoned. The new vault will rest entirely on piers and arches of masonry so that the watchman can, at all times, pass under it and inspect the bottom of it.

The walls of the vault are 6¼ inches thick and are built up of alternate layers of iron and chrome steel welded together. Everything about the vault is made to guard against the possible use of explosives. Each of the three compartments contains seventy steel strong boxes which will hold the gold, currency and securities which it is necessary to deposit. The Clearing House is now constructing a new building in which the vault will be erected.

AN IMPROVED PIANO ACTION FRAME.

This is a frame of simple and durable construction, arranged to firmly hold the actions in position and prevent loosening of the arms carrying the pivots for the hammers, dampers, and other parts of the action. It has been patented by Mr. Frederick W. Bothmer, of No. 803 Tenth Street, Long Island City, N. Y. A number of metal brackets are secured in the usual manner to the piano frame, at equal distances apart, and on the rear of the brackets are secured, by machine screws, the rails, A, B, as shown in Fig. 2, a sectional view through the entire action being represented in Fig. 1. The rails are connected with each other by short arms




BOTHMER'S PIANO ACTION FRAME.

whose upper ends engage a longitudinal groove in the under side of rail, A, their lower ends being seated in a similar groove in the top of rail, B. In the top of rail, A, is also a ridge adapted to enter a groove in the under side of an arm which forms at its inner end the pivot for the hammer, and at its outer end the pivot for the damper, of the particular action for a single string. On the under side of rail, A, are also lugs engaged by pivot arms of the damper bar, adapted to be actuated in the usual manner from the pedal, and on the rear of rail, B, is a ridge engaging a recess in an arm which carries a lever actuated from the piano key, the two rails, which are made of metal, thus forming firm supports for the pivoted arms, so that a displacement of the hammers and dampers and other parts of the action is not likely to take place.

A STREET CAR RAIL SWEEPER.

It is quite necessary for the wheels of electrically propelled cars to continuously make good contact with the track rails, and to insure this, as well as to facilitate the cleaning of street railway tracks generally, is the object of the improvement represented in the accompanying illustration. It has been patented by Mr. Thomas Waite, of Cramer Hill, N. J. A transverse shaft journaled in the outer end portions of the car, and adapted to be rotated by a chain belt from the car axle, carries near each outer end a loosely mounted sleeve, and integral with each sleeve is a hanger in which a brush is journaled diagonally over the rails, as shown in the small view. On the inner end of each brush spindle is a beveled gear meshing with similar gears on the ends of the transverse shaft, and the hub of the pinion on this shaft, over which passes the chain belt, has a clutch face adapted to engage with a clutch connected with a shifting lever operated by means of a rod terminating in a handle at



WAITE'S RAILWAY RAIL SWEEPER.

one side of the car, whereby the driver or motor man may readily throw the clutch into or out of gear. The two hangers carrying the brushes are connected by a rod, and an elbow lever loosely mounted on the drive shaft has one of its members connected to this rod, while the other member is pivotally connected with a link from which a hand lever extends up through the car platform. By means of this lever the brushes may be elevated to be carried along above the track or thrown down to engage the rails, the clutch on the drive shaft being correspondingly moved into or out of engagement with the pinion driven by a chain belt from the gear on the car axle.

The Use of Quebracho in Tanning.

According to a recent German trade report, the German tanners are now adopting the use of quebracho and other tanning materials, such as divi-divi, myrobalanus, japonica, mimosa, valonia, alogobilla, etc., in place of oak bark. The leather industry in Germany has shown great progress in recent years, and the new tanning material of quebracho has produced a revolution in tanning upper and sole leather. Quebracho is now used all over Germany and in other countries on the Continent. Quebracho wood is imported principally in logs and on sailing vessels. It came originally from the province of Santiago, in Chile, but this source of supply is gradually becoming exhausted. In recent years, in the Argentine Republic, extensive forests of quebracho have been opened. Of quebracho, two varieties are known, the red and the white. Red quebracho is richer in tannin than the white, the average contents being from 18 to 20 per cent. Considering the intrinsic value of this tanning material, it is cheaper than oak bark, and nearly as cheap as hemlock. Owing to its very high percentage of tanning qualities, quebracho contains relatively a small proportion of so-called non-tanning substances, and in this respect it has much resemblance to gambier.

These non-tanning substances are an important factor in the manufacture of leather, as they fill and nourish the leather, and also impart the necessary acidity to liquors, although not assimilating in a direct manner with the fiber of the hide. Quebracho, it is stated, does not possess a sufficiency of these non-tanning properties to yield well nourished leathers, and its use, therefore, is only to be recommended in combination with other agents stronger in non-tanning substances. The supply of quebracho may be considered inexhaustible. Nearing the thirty-first degree of longitude in the Argentine Republic, the Pampas, the largest grazing lands known to the world, gradually develop into immense forests known as chaco. The chaco is wonderful for its luxuriant and varied vegetation; within its limits are found all kinds of tropical trees—among these in abundance the red and white quebracho. The red quebracho, like all other trees found in these regions, with the exception of the palm, does not attain a great height, although the trunk is well developed. Of a reddish brown, this wood is heavy and hard, and has tanning qualities which of late years have become highly appreciated in Europe. Formerly quebracho wood was obtained only from the forests bordering on the Parana River, but now transportation by rail is possible, and gigantic saw milling enterprises have been started which develop the untold wealth of the chaco and send their products to market.

It is stated that the tract of country can furnish a fabulous amount of quebracho wood, practically an inexhaustible amount, while the present yearly consumption is but one million tons. Ten years ago the exports of wood from the Argentine Republic aggregated in value £15,000; during 1892 this value had increased to £300,000. Very recently a saw mill has been erected at each of the ten railway stations between Rosario and Beurequiste. The government allows the privilege of cutting timber within its boundaries, but makes no grants for more than 13 leagues. One league of forest in the vicinity of the railway is considered worth from £1,500 to about £2,000. On the value of the woods arriving at the sea a tax of 3 to 7 per cent is levied. The unlimited supply and low cost of production make quebracho wood one of the cheapest vegetable tanning materials known. About one hundred blows with an ax and a few hours' labor spent in peeling the bark and sawing the logs suffice to secure a ton of wood, whereas it is estimated that about 150 working hours are required to supply a ton of oak bark. The grinding and cutting of quebracho wood is naturally a more difficult operation than getting out hemlock or oak bark, but considering the original cost, this is relatively an unimportant item.

Transportation from the Argentine Republic to Europe can be effected so cheaply that many firms ship their rough lumber to Europe to be worked into extract there. The red quebracho contains in considerable quantity a red coloring matter, which is hardly soluble in cold water, but will dissolve readily in warm water. For this reason quebracho extracts, if not properly treated, will impart a reddish tint to leather. Used alone quebracho extract will only yield a leather of poor color, but when combined with alum and salt it yields finer results even than gambier. Leather tanned with quebracho, alum, and salt has a pale straw yellow appearance, the flesh side being almost white. In first using quebracho extract it is important to use much weaker liquors than those needed with other tanning agents. There are large extract works in Reuners and Benrath, near Hamburg; also in Oberlahnstein on the Rhine, and Frankfurt-on-Main. In these factories the wood is cut by machines specially built for that purpose. It is cut from the log in two different ways—side and head cut. The side cut is of fine, thin, small chips, up to about one inch long, and the head cut consists of smaller and coarser pieces. Quebracho extract is manufactured in crystal and soft

paste. The crystal is put up in cases of 150 kilogrammes (330 pounds avoirdupois) and costs about £2 15s. It contains about 65 to 70 per cent of tannin. The paste is put up in barrels of from 230 to 250 kilogrammes (506 to 550 pounds avoirdupois) and contains about 45 per cent of tannin.

BRINER'S ASH SIFTER.

This is a sifter of very simple and inexpensive construction, which may be readily attached to or detached from an ordinary ash can or barrel, altogether preventing the escape of dust or other fine particles while sifting the ashes. As shown in the illustration, applied to an ash can of moderate size, the sifting may be done at the side of the stove or range from which the ashes are removed, rendering the device of especial convenience in flats or apartment houses. The improvement has been patented by Mr. Emil Briner, of 54 Rutgers Street, New York City. An open-ended bag of sail duck or other suitable canvas is attached by means of a draw string to the mouth of the can, a second draw string drawing the bag closely over and in from the edges of the can, to absolutely prevent the escape of any dust, and cause the ashes to readily fall into the can. The upper end of the bag is attached by means of another draw string to a circular head in



which is a sieve, and a cover is adapted to be set on the head during the sifting operation, as shown in one of the views.




The Lead Wort.

The lead wort, or *Amorpha canescens*, with its tall, lavender spikes of flowers is found in the dry regions of the Rocky Mountains. It is said to prefer localities where lead exists, whence its name. The effect of the beautiful purplish hue of the blossoms is enhanced by the golden spangles of the yellow anthers among them. The anther cores become bleached after the pollen has been shed and still further add to the beauty of the plant. The anthers mature one after another, the first one out being a little larger than the rest, and not until the last stamen has been fully formed does the small vexillum finish its growth. This is thought to account for its amorphous character.

The lateral growth remains stationary until the axial growth is complete. It then commences, beginning at the apex and continuing downward. Thus the spiral growth uncoils backward, and axial development ceases when the vexillum has been reached.

A SIMPLE HAIR CURLING DEVICE.

This is an inexpensive implement affording a guard for the hair as it is wrapped on the hot iron and obviating liability to burn the fingers. It has been patented by Mr. Edward J. Brand, of No. 61 Fulton Street, Columbus, Ohio. It has two pivoted limbs, one of which is adapted to close upon the other, and a diminished shank of one limb extends through a central recess in the handle piece, at the outer end of which it terminates in a crank handle. One of the limbs is furnished with curved guard wings, and a spring attached to one wing bears at its other end on




BRAND'S CURLING IRON.

a ferrule of the handle, the spring normally holding the limbs closed. On the outer end of the wing to which the spring is attached is a button to protect the hand in manipulating the device when heated. As will be seen, the implement may be readily heated by being hung in the chimney of a lighted lamp, or such other manner as desired.

In an article in the June number of the *Astrophysical Journal*, by H. Ebert, he concludes that the temperature of the interior regions of the sun is in round numbers 40,000° C. This is in good agreement with values previously determined by others.

AN AUTOMATIC BRAKE SLACK ADJUSTER.


The illustration represents an improvement designed to automatically take up all the slack in the brake mechanism caused by the wear of brake shoes, permitting a uniform travel of the piston in the brake cylinder and insuring a full and effective pressure in the air brake cylinder at the time the brakes are applied. The

**FREESE AND NICHOLSON'S BRAKE SLACK ADJUSTER.**


improvement has been patented by Messrs. William De Freese and Thomas E. Nicholson, No. 1296 Topping Street, Hamline, St. Paul, Minn. The brake rod is connected at one end, as usual, with the piston in the brake cylinder, and at its other end with the brake lever, which is connected by a link with the dead brake lever. The latter is pivotally connected, as shown in Fig. 1, with a head in which is held adjustable a rod connected with a longitudinal toothed bar sliding in bearings in a casing, the teeth of the bar being engaged by gravity dogs, of which one has its fulcrum in the casing, while the fulcrum of the other extends through slots into the casing, to engage the forked ends of a lever fulcrumed at its lower end on the casing, as shown in Figs. 2 and 3. Through the upper end of the lever the brake rod passes loosely, lugs being held on the rod at opposite sides of the lever. Near its lower end the lever is pivotally connected with a spring which holds the lever normally in the position shown in Figs. 1 and 3. When from wear of the brake shoes or other cause a slack exists, and the piston in the brake cylinder has to travel beyond its normal stroke, the brake rod is drawn or pulled a greater distance to properly apply the brakes, and one of the lugs on the rod then engages the free end of the lever, swinging it until its dog engages the next tooth on the toothed bar. When the brakes are released and the lever is returned to its normal position, the toothed bar is moved by the dog into engagement with the other dog, which has its fulcrum in the casing, the toothed bar thus taking up any slack in the brake mechanism. The device works automatically and the bar is sufficiently long to take up all slack until the brake shoes are completely worn out.

THE BUNDY STEAM TRAP.

This trap has no interior float. It is operated by the power developed by the weight of the water that collects in the bowl. When the bowl is filled, then the weight of the water, in addition to the weight of the bowl, overbalances the ball weight on the lever, and the bowl settles in the frame, thereby opening the live steam connection from the top of the boiler to the trap. Upon the admission of live steam from the boiler to the trap the check valve in the pipe leading to the trap is immediately closed and temporarily the trap becomes a part of the boiler, subject to the same steam pressure and water line, and hence the water in the trap at once enters the boiler, passing a check valve placed between it and the boiler, on both sides



TANK TRAP.



RETURN TRAP.

THE BUNDY STEAM TRAP.

of which, the steam pressure not being equal, the water of its own weight opens the check and passes in.

After the bowl has emptied itself into the boiler it again becomes sufficiently light so that the ball weight on the lever overbalances it and the bowl is rolled in the frame and the live steam valve is closed, at the

same time an air valve underneath the steam valve is opened to allow the escape of any air or vapor that may enter the bowl. A special feature of this trap is the fact that on the air valve pipe a horizontal check valve is used, so that while there is a vacuum in the trap bowl the check remains closed and the vacuum helps to fill it again with water.

The Bundy traps are made in four sizes, holding from five to fifteen gallons of water. They are made by the A. A. Griffing Iron Company, Jersey City, N. J. In the bowl of the return trap there is a bent pipe turned up that is screwed into a diaphragm at the smaller end of the bowl, while the other end terminates near the highest point of the bowl. The live steam upon entering the trap is directed through this bent pipe and so brings the pressure upon the top of the water in the trap. Our illustration shows this feature.

In the Bundy tank trap it will be observed that this bent pipe extends downward from the diaphragm to the lowest part of the bowl, and so, when this trap is discharging, the water is forced up through this pipe and so on out through the discharge valve.


Before all the water is discharged from the tank trap it is so adjusted that the trap bowl will rise in the frame and the discharge valve be closed, so that at no time is the end of this pipe out of water. The water covering the pipe at all times prevents the escape of any steam.

When one takes into consideration the adaptability of steam traps, it is not at all surprising that thousands of these traps are sold, and that so many factories have from one to fifty in use. They may be used as a boiler feed in place of a pump.

THE IMPROVED BELL ODOMETER.

The carriage odometer shown in the engraving accurately registers the distance traveled, and will record and ring a tiny bell as each mile is passed.

It is actuated by a steel pin driven into the hub. This pin engages the spur wheel, shown on the right of engraving, at each revolution of the carriage wheel. The spur wheel is attached to a worm shaft extending through from right to left. Engaging with this shaft is a cut brass gear, termed the unit wheel, mounted on a central shaft extending from the dial plate to the rear. The varying sizes of carriage wheels are compensated by the size of this unit wheel. Keyed to the



central shaft is a pawl which sets in motion the internal gears, and these are connected by bushings to indexes on the dial. This pawl is so constructed as not to propel the gears when reversed, thus avoiding all danger of injury when the carriage is backed. With this exception the entire movement is positive and quite accurate, regardless of speed on uneven ground. Attached to the central shaft, back of the case, is a small gong which is struck a smart blow with a spring hammer at each revolution, thus announcing that a mile has been passed.

The dial contains three indexes, each of a different color. The red index registers a mile at each revolution, and, as the dial is divided into forty spaces, each space represents the fortieth of a mile, or eight rods. The yellow index revolves once in forty miles, and each space represents a mile. The blue index revolves once in 1,600 miles, so that each space represents forty miles in relation to this index. The figures inside the

ring indicate miles, measured by the yellow index, while the figures outside the ring indicate miles, measured by the blue index. The dial thus constitutes a reliable record of the distance traveled. On starting out, the positions of the indexes may be quickly marked on a dial card—a number of which are furnished with each odometer—and on returning from a drive the distance traveled may be seen at a glance. The dial is protected by a heavy watch crystal, secured

by brass bezels screwed in the malleable case. The whole is protected by a neat nickel-plated hood.

It is now less than two years since this instrument was placed on the market by Messrs. Davis, Stebbins & Company, 33 Sudbury Street, Boston, and the result has been very gratifying to its introducers, numbers of


them having been sent to nearly every State and Territory, to the Provinces and to Mexico.

Meteorological Balloons.

A balloon equipped with self-registering instruments to measure the temperature and pressure of the atmosphere at high altitudes was recently experimented with in Berlin and came down with the instruments in good condition in Bosnia. The instruments showed that the balloon had reached an elevation of 53,872 feet, over 10 miles; the thermometer had fallen to 52 degrees below zero—the lowest it could record. Another balloon sent up later is stated to have reached an elevation of 72,000 feet above the earth, or 13½ miles.

A BICYCLER'S DISTANCE RECORDER.


This compact little measurer of distance traveled



ACTUAL SIZE

THE "TRENTON" CYCLOMETER.

by a wheelman, shown herewith detached and applied to a wheel, weighs only 2¼ oz., and registers up to 1,000 miles and repeats. It is made of aluminum, with a satin finished dial which presents a handsome appearance and will not break or crack. It is manufactured by the Trenton Watch Co., of Trenton, N. J., who have admirable facilities for the production of such work in a manner which shall insure absolute accuracy. This cyclometer is noiseless and positive in action, while being also dustproof and waterproof. It can be run backward and forward at the highest rates of speed without the possibility of injury. All instruments before being sent out are tested in a lathe running at many times the speed they will ever be called upon to record on a wheel. One instrument was thus run over one hundred and thirty thousand miles, recording at the average rate of a mile in four seconds, without showing the slightest evidence of wear, and the same instrument was run backward at equal speed. As will be seen from the illustration,

**THE "TRENTON" CYCLOMETER.**

it is but a matter of a moment to apply the instrument to a wheel, and its dial can be read at a glance from the saddle.

The New York Botanical Garden.

Under the act of incorporation, the citizens forming the society known as the "New York Botanical Garden" have subscribed \$250,000 as an endowment fund, and the Department of Public Parks is authorized to set apart a portion of Bronx Park, not to exceed 250 acres, for the purposes of the botanical garden. The city will also appropriate \$500,000 for the construction and equipment of buildings. Bronx Park is about two miles in length and half a mile in width and contains 653 acres; it extends along both sides of the Bronx River, in the northern part of the city. In the botanical museum will be collected specimens of the products of plants. This building will contain laboratories, lecture rooms and an herbarium, which, it is hoped, will ultimately contain specimens of all known plants. There will be a large number of greenhouses of various sizes, which will contain a great variety of growing plants from tropical countries. In the outdoor department will be as large a variety of plants as will grow in this climate; also an arboretum, in which all the trees that can endure our climate will be grown.

The average speed made on the recent 1000 mile relay bicycle race, Chicago to New York, was 15½ miles per hour. Michael, a young Englishman, on May 19, at Paris, made 100 miles in 4h. 2m. 45½sec.

THE BLAKE REPEATING RIFLE.

This rifle was, in its military model, one of those submitted to the United States Army Board on Magazine Arms which reported May 20, 1893. It also was brought before the Navy Board on Small Arms in May of the present year. The inventor and maker is Mr. John H. Blake, of No. 136 Liberty Street, New York. The arm was favorably spoken of by both the Army and Navy Boards, but the radical departure of the magazine system from any known system or any system before either board, made it almost too much of an innovation to be hastily recommended for adoption. Since these tests, sportsmen and rifle experts have encouraged the inventor to put it on the market slightly modified to conform to sporting requirements, the cut showing the sporting model. The system is that technically known as a "multiple loader revolving packet repeating rifle."

It is a "central" magazine rifle that by the use of a "cut-off" can be used as a rapid single loader, with magazine holding seven cartridges in reserve, available as a repeater whenever the cut-off is thrown in. Single loading fire can be resumed at any time, holding the remaining cartridges in packet in reserve. It is said that an expert is able to fire at the rate of 43 shots per minute until his ammunition supply is exhausted.

The distinctive feature of the system is that of the cartridges being carried in the belt or pockets in a revolving cylindrical packet, holding generally seven cartridges. These packets are charged into the magazine, which lies under the receiver and just forward of the trigger guard, in one movement and "en bloc," as if the packet were a single cartridge. The cartridges are fed into the chamber by a positive movement, and when the cartridge packet is empty, the magazine door is opened, the empty packet drops out and a full packet is recharged. An empty packet may be refilled with cartridges many times, if desired; the packet weighs less than two ounces and can be furnished for a few cents.

The rifle holds eight cartridges, one in the chamber and seven in the magazine. Two more packets may be carried in a vest, or shooting jacket, lower pocket, which would give a supply of twenty-two cartridges. If it is thought desirable to carry more cartridges, more packets may be carried in the pockets, or in loops on the cartridge belt as those now in use, the loops merely being larger. A full belt would hold fifteen packets. A belt may have a smaller number of loops, the rest of the belt being looped to carry single cartridges.

The action is that of the bolt system. In the sectional view showing the action open, the receiver has on its left hand side a broad and deep groove, a, for the passage of the left locking lug of the bolt, and on the right a shoulder for the extractor and right locking lug of the bolt. The entire bottom is cut away to permit the upward and forward movement of cartridges from the magazine. The forward breech casing contains the grooves for the locking lugs of the bolt, and on the right hand a cut for the hook of the extractor. At the rear the breech casing for a short distance is closed at the top, completely encircling the bolt; back of that a channel is left for passage of the handle, while at the right a shoulder is formed, in front of which the base of the handle locks in the firing position. The magazine casing consists of a cylindrical box placed below the receiver. A central section of it is shown in the small figures, the upper view representing the cartridge packet adjusted for magazine fire and the lower one with the magazine in reserve. Its bottom is hinged at the left side, d, and when closed is secured by the catch, e f. The cartridge packet has at the front and rear ends trunnions, which rest in beds in the front and rear faces of the casing.

The action of this rifle is built strong enough to shoot the $7\frac{1}{2}$ millimeter, or 0.30 cal. U. S. army smokeless rifle cartridge at a muzzle velocity of 2,000 feet per second, which gives a chamber pressure of twenty tons per square inch; and also the 6 millimeter, 0.236 cal. U. S. navy cartridge at a muzzle velocity of 2,500 feet per second, giving a chamber pressure of thirty tons per square inch.

THE splendid lake steamer, the Northwest, recently made the trip from Milwaukee to Chicago, 86½ miles, in 4 hours 6 minutes, being at the rate of 21.13 miles per hour.

How to Ride the Wheel.*

In the course of a paper on "Cycling as a Pursuit," F. W. Shorland, an English bicyclist, has set down a number of hints on riding that beginners will find very helpful. As the recent impetus the sport has received has brought out many new devotees of the wheel, we reproduce here a portion of Mr. Shorland's article.

Cycling as a pleasurable pursuit ceases to be enjoyable when it becomes sheer hard work. In nothing is it so easy to make a toil of pleasure, and therefore my strongest advice to every one indulging in the pastime is to take it easy and not to overdo it. This is, of course, a personal matter entirely. One man's pottering pace is another man's high pressure effort, and I have often noticed how inferior riders will utterly ruin their enjoyment of a run by dreading to acknowledge that they cannot keep up as high a rate of speed as other men with whom they may happen to fall in during a spin upon a frequented road.

Be very careful of strange cyclists. You never know whether they are able to ride or not, and the wobbles of a novice are the most dangerous obstructions of the highway. Even one's own companions are sometimes the cause of collision, especially if they are not used to riding in company. One man can squeeze through a tight place where two cannot, and it is customary for men not used to riding at close quarters to cut in front very dangerously.

In all road riding it is a good plan to avoid sudden changes and violent alterations of pace and course. For instance, in passing a cart it is much better and safer to take a long swing round it than to swerve sharply behind and to return to one's course immediately in front of it. A sudden and jerky style of riding is the usual cause of slipping sideways on a wet and

sible a continuously even driving pressure, one foot taking up the strain before the other ceases to drive.

Although steering and pedaling are so closely related in this respect that it is impossible to steer well when one pedals badly, yet that is not the whole secret of good steersmanship. No one is a good steerer who cannot ride a "safety" with his hands off the handles. I do not advise this style of riding, which is merely the showing off of a really very simple accomplishment, but what I mean is that the ability so to steer shows that one's steering has been mastered. It is only a matter of a few trials, provided one's machine has its frame true and its wheels in line. It means that the rider has escaped from the elementary and erroneous impression that his handle bar is something to keep a tight grip on.

Aching wrists and blistered palms are proofs of bad steering. Handles do not want to be grasped like a try-your-strength machine; they are, when steering is mastered, simply hand rests, and a light touch is all that is needed. Pulling at the handles and wrenching the front wheel about is all wrong. For very stiff hills it is useful as a change to pull at the handles, but when a hill is severe enough to need this style of riding it is wisest to walk.

The third point of importance in style is the position; that is, the relative positions of the handles, saddle, and pedals. The center of the crank axle, to which cranks and pedal are fastened, is a fixed point in the machine, and the handles and saddle are equally adjustable; so it is convenient to measure from this fixed point, and when one's own fit is found, to keep a memorandum of it. A very suitable medium position for all-round work is to have the peak of the saddle just so far back that a vertical line from it hangs

against the pedal when at its rearmost position. In the old days of the ordinary, a very vertical position

right over the work was assumed, and a reaction set in on "safeties," exaggerated immensely on front drivers to a ridiculously far-back position of 14 inches or more, both of which extremes are wrong. The further one sits forward the higher can one's saddle be raised, and in a very far-back position a rider has always to be doubled up, and cannot sit in comfort.

The reach is best determined by noticing, when riding, whether at the bottom of the stroke you can, while keeping the foot in position on the pedal, drop the heel to the lowest possible extent and then find the leg straight. The leg


should never be fully extended at any point of the revolution. That is why if at the lowest part of the stroke you exaggerate the position of anking, and then find the leg straight, you may be certain that for riding purposes you are, as you should be, just within your reach. In any case, it is a far less serious error to be too short than too long.

Handles should be so adjusted that they can be easily reached when sitting in a comfortable posture; not so high that the arms are akimbo, and not so low that a humped-up attitude is enforced. Bicycle hump and a crouched-down stoop are only necessary at sprinting pace when windage is excessive. The majority of the stoops and humps seen on cyclists are due to the rider having his handles too low and trying to sit up to an easier position. A bicycle rider should not copy either a piano player or a man pulling up weeds; he wants his hands about level with his knees when his thighs are horizontal. If they are up too high, he does not get the best results or have as accurate a control of the steering; but even that is better than being folded in half on the machine by an outrageously dropped handle bar.


Street Car Fenders.

A correspondent says: A properly constructed bale or cushion filled with flocculent or equivalent material and of suitable size and shape and restrained from materially yielding otherwise than backward, and arranged to lie or be adjusted in proximity to the track, would, if carried by the car in front, be much more efficient, prevent injury to limb, and be more certain in its action than a metal fender in pushing a body before it on the track or out of the way of harm till the car could be stopped. It is a simple expedient, but often simple means are the most reliable.


THERE are over seven miles of tunnels cut in the solid rock of Gibraltar.



THE BLAKE REPEATING RIFLE—SPORTING MODEL.



THE BLAKE RIFLE—ACTION OPEN.



greasy road. Of course, there are certain conditions of road when the most expert riders cannot avoid slipping, especially with plain-faced tires; but these states of greasiness are exceptional, and most side slipping is due to spasmodic instead of smooth pedaling, to bad steering, and a wrong position.

Bad pedaling is a very common defect in the average rider. No man can race successfully without pedaling well; but the average rider who only uses his machine for pleasure would be astonished at his increase of enjoyment, if only he took the trouble to learn to pedal smoothly. It is noticeable, in nine cases out of ten, that the chains of ordinary riders are not kept continuously tight on the driving or upper part. Smooth pedaling, with continuous pressure, will change all that. Backlash should never be permitted, as it is evidence of a slovenly, wasteful style, besides being a very frequent source of slipping.

A smooth, continuous style of pedaling gives one a firm seat on the machine and helps the steering. Every one knows that in slowing a bicycle by back pedaling the conditions of steering are different from those of pedaling forward; if, then, a rider by uneven pedaling introduces a little back pedaling every revolution, he is continually varying the conditions affecting the steering, which consequently is erratic, if not dangerous. Smooth pedaling and a straight course go naturally together, yet the majority of trails one sees are wonderful loopy and zigzag; clear proofs of the prevalence of uneven driving and the consequent indifferent steering.

Alternate plugging on the pedals is hopelessly wrong, and the first aim of any one who wants to ride well should be to get his feet round evenly, not to raise one by the down push of the other in jerks, but by dropping the heel at the bottom of the stroke and, as it were, gripping the pedal, to maintain as near as pos-

* From the National Popular Review, originally in the Argonaut.

Correspondence.

Oil, Gas and Water from an Artesian Well.

To the Editor of the SCIENTIFIC AMERICAN:

Under promotion of this club and with the purpose of developing a water supply for this city the first one of three artesian wells has about been completed. It presents conditions which are believed to be novel and of general interest.

The well is 2,487 feet deep and flows about 300,000 gallons of water each twenty-four hours, the initial pressure being 65 pounds and the temperature 120 degrees Fah. There is a double casing from the top to a depth of 2,200 feet, one being 4½ inches (and through it only the water flows) and the other 6 inches in diameter. The 4½ inch pipe then continues to the top of the water-bearing stratum, about 2,400 feet. The water as it appears is strongly mixed with natural gas which readily ignites, so that apparently water and flame flow from the same opening. Scientific analysis shows that the water is impregnated with mineral properties in the proportion as shown below per gallon:

Sodium chloride	226.71 grains.
Sodium carbonate	69.50 "
Calcium bicarbonate	4.31 "
Other solids	2.25 "
Total per gallon	302.77 "

The water has been turned directly into the mains of the public water supply system of the city, and readily furnishes a fine fire pressure, besides filling the stand-pipe 100 feet high on a neighboring elevation. The gas in the water is a matter of some embarrassment, and it is a problem with us as to how to dispose of it.

Another point of especial interest is that, at a depth of 1,050 feet, a flow of petroleum oil was struck, which has been of the greatest trouble in prosecuting the work, the entire boring plant having been twice consumed by fire on account of it. The flow is remarkable in that it has appeared with a persistent and uncontrollable natural or artesian flow of about 70 gallons a day, and this has continued for nearly a year. A rupture having occurred in the 6 inch pipe, the oil has found it, and now flows between the inner and outer casing of the well with a velocity very much accelerated by the high temperature of the inner pipe.

What to do with the oil and with the gas, and how readily to separate the latter from the water and to utilize the same, are problems which very much puzzle us amateurs, and if they are such as interest the scientific, we would be glad of any suggestion from you or your readers. We think we have one of the most remarkable deep artesian wells in the world.

COMMERCIAL CLUB.

Corsicana, Texas, June 12, 1895.

Cost of Power at Niagara.

The company which has undertaken to develop electricity at Niagara, on a large scale, for manufacturing and other purposes, has acquired more real estate there than it needs for its own use, in order to furnish sites to such of its customers as wish to establish their business close to the source of their mechanical power supply. But the public has been led to expect that in addition to serving local interests, the company would also furnish electricity to places scores, if not hundreds, of miles away, and there has been much speculation as to the feasibility of carrying such plans into effect. Owing to her proximity to the Falls and her great size and industrial activity, Buffalo has been regarded as the first center of population, removed from Niagara, to be provided for. It is not yet quite clear whether that city feels that it is enjoying a privilege or conferring a favor in letting the power company invade its precincts. Perhaps she has not determined that point herself. The matter is evidently still under consideration. In reply to some inquiries from representative Buffalonians, the Power Company recently offered the following terms:

It would let the municipality or a private corporation come to Niagara, take water from the Power Company's canals at the rate of \$10 a horse power, and manufacture its own electricity; or it would furnish power off the turbine shafts at \$13, or electricity at the power house at \$18. But if the Power Company undertook to do anything of this sort, it would not contract to deliver less than 10,000 horse power. Hence Buffalo must agree to take at least that much or none at all. The Niagara people would not accept a franchise to operate a line to and in Buffalo for a shorter time than that for which its own bonds have been issued. No price is given for electricity delivered at a central station in the suburbs of that city, fifteen miles from the Falls, so that the company's own estimate of the probable waste and cost of transmission is still withheld.

There would be four kinds of losses: (1) In transforming at the power house up to a high voltage, (2) on the line, (3) in transforming down at Buffalo, and (4) in distribution over street lines to consumers. These could not well amount to less than 20 or 30 per cent altogether, and they might, perhaps, reach 50 or 60 per cent. But if, for example, they amounted to just one-

half, the \$18 rate at the generator shaft would mean \$36 to the consumer, without adding anything either for interest on the cost of the transmission plant or for operating expenses. This, however, is probably an extravagant estimate. The prices actually given, by the way, are for a twenty-four hour daily supply. Some establishments require power, however, for only ten or eleven hours. Whether it would pay to put in storage batteries to utilize the surplus is a question which their managers must naturally consider.

Richard Hammond writes to the Buffalo Courier to say that steam power, on a scale of 1,000 horse power for ten hours daily, can be generated in Buffalo, where coal is very cheap, for \$21 per horse power. The Power Company, however, denies this, and estimates the cost at \$32, besides quoting various experts as estimating the cost on a twenty-four hour basis at between \$45 and \$60. In some other cities, where coal is more expensive, it is said to be from \$60 to \$75. If, after this discussion, Buffalo decided neither to buy on the terms offered nor to let the Power Company bring in its own lines and supply the market, more distant cities may possibly be deterred by her example from patronizing the Niagara concern; but as the latter supplies its local customers with electricity at \$20 per horse power, in large quantities, there may be a greater industrial development at the Falls than would otherwise result. —New York Tribune.

Electrical Notes.

Benjamin Franklin on Torpedo Fish.—An interesting letter of Benjamin Franklin on the stroke of the so-called torpedo fish is preserved in the electrical department of the Armour Institute, Chicago. It was written during Franklin's second mission to England, while he was engaged in devising means for protecting the powder magazine at Purfleet from lightning. He was very busy at this time and was, besides, involved in a bitter political quarrel with Lord Hillsborough, the Secretary of State for the Colonies; but he, nevertheless, found time to study torpedo fishes and their effects.

The letter is indorsed: "Franklin's Instructions to Try if the Stroke of the Torpedo be Electrical," and is, in full, as follows:

It has long been supposed that the Stroke given by the Torpedo was the Effect of sudden violent muscular Motion. It is now suspected to be an Effect of the Electric or some similar subtil Fluid which that Fish has the Power of acting upon and agitating at Pleasure.

To discover whether it be the Effect of a subtil Fluid, or of Muscular Motion, let the Fish be touch'd with the usual Conductors of Electricity, viz.:—Iron, or other Metals; and with the known Non-Conductors, dry Wood, Glass, Wax, etc. If the Stroke be communicated thro' the First and not the Latter, there is so far a Similarity with the electric Fluids, and at the same Time a Proof that the Stroke is not an Effect of mere muscular Motion.

Let it be observed whether the Stroke is sometimes given on the near Approach of a conducting Body without actual Contact; if so, that is another similar Circumstance.—Then observe whether in that case any Snap is heard; and in the Dark any Light or Spark is seen between the Fish and the approaching Body. If not, there the Fluids differ.

Let a Number of Persons stand on the Ground, join Hands, and let One touch the Fish, so as to receive the Stroke. If all feel it, then let him be laid with his Belly on the Plate of the Metal; let one of the Persons so joining Hands touch that Plate, while the farthest from the Plate with a Rod of Metal touch the Back of the Fish; and then observe whether the Force of the Stroke seems to be the same to all in Circuit as it was before, or stronger.

Repeat the last Experiment with this Variation. Let two of the Persons in the Circuit hold each an uncharged electric Phial, the Knobs at the Ends of their Wires touching. After the Stroke, let it be observed whether those Wires will attract or repel like Bodies, and whether a cork Ball suspended by a long silk String, so as to hang between the Wires at a small Distance from the Knobs of each will be attracted and repelled, alternating to and from each Knob; if so, the Back and Belly of the Fish are at the Time of the Stroke in different States of Electricity.

London, August 12, 1772.

B. FRANKLIN.

The Slaviano Electric Welding Process.—The Slaviano system of electric welding, or the Slaviano smelting system, as its inventor calls it, is coming into extended use in Europe, and has been for some time in successful operation in the celebrated Perm Gun Works in Russia. It is said to be an improvement on the well known Thomson and Benardos systems. Its principle depends upon the employment of a bath and the development of hydrogen at the negative pole, surrounding the part to be welded. The gas thus forms a high resistance to the current at this point, producing a corresponding amount of heat, which is communicated to the negative pole. A supply of molten metal, of the same character as the object to be welded, is supplied to the fractured part. This is accomplished by using the object operated upon as one electrode and a bar of

the same metal as the other. During the welding this bar is gradually melted down and constantly supplies metal to the fracture as it is needed. A spring and solenoid automatically regulate the feed.

The Slaviano process is, it is said, applicable to all ordinary metals. Some remarkable work has already been done by it at the Perm works. Some of the fractures repaired without difficulty were such as would have offered almost insuperable obstacles to any other known system. One of these was a bell about six feet in height and in its greatest diameter that was cracked from top to bottom. Another was an immense roll from a rolling mill broken in two near the center.

Measuring Specific Inductive Power.—A new method for measuring specific inductive power has been described by Mr. Nodon and Prof. Pellat. They employed two metallic spheres of small capacity, placed some distance apart and connected with an induction coil, and a third, movable, sphere grounded through a telephone. This third sphere is placed between the other two, its position being determined by the point at which no sound is heard through the telephone.

The dielectric to be tested is placed between one of the stationary spheres and the movable one, and the latter is moved toward the dielectric until the telephone again becomes silent. The distance between the first and second positions of the movable sphere will then be proportional to the specific inductive power of the dielectric. In using the apparatus a material whose inductive capacity is known is first used; the unknown substance is tested from this or a standard. The two specific inductive capacities will be directly proportional to the distances found in the two tests.

Electricity from Heat.—M. Desire Korda, a French electrician, has recently made a thermo-chemical galvanic cell, using ordinary gas retort carbon and a few cubic centimeters of barium peroxide. The salt is simply placed upon a flat piece of the carbon and the latter is heated to redness in a gas flame. A violent effervescence takes place and carbonic acid is given off. A voltmeter, whose terminals are connected by means of platinum wires with the carbon and the salt respectively, shows a deflection indicating a difference of potential of about one volt.

If cupric oxide, resting upon a layer of potassium carbonate, be used instead of the barium peroxide, a voltage of 1.1 is indicated.

Dynamo and Steam Engine Efficiency.—Prof. Unwin complained, in a recent lecture, that electrical engineers were in the habit of comparing the efficiency of the dynamo with that of the steam engine, greatly to the discredit of the latter. It is a common saying, he adds, that the efficiency of a dynamo is from 90 to 95 per cent, while that of the steam engine is only about 10 per cent; but this comparison is an unfair one, and shows a lack of comprehension of one of the two fundamental laws of thermodynamics, namely, the law of the motivity of heat. Heat energy is undirected energy and only a fraction of it is convertible into mechanical energy. Working, as it must, with only this available fraction, the steam engine is not an inefficient machine. The task of the dynamo is simpler. Electricity is directed energy in a wholly convertible form, and it is, therefore, only necessary to transform one kind of directed energy into another. In order to do this, only a small fraction need be wasted. Prof. Unwin says further that the electrical engineer is to blame for his ingratitude, as without the steam engine the dynamo would be but a useless mass of metal and wire.

Silvering Glass.

A simplified process for silvering glass is thus described by MM. Auguste and Louis Lumiere, in the Journal de Physique. Take 100 parts by volume of a 10 per cent solution of nitrate of silver, and add, drop by drop, a quantity of ammonia, just sufficient to dissolve the precipitate formed, avoiding any excess of ammonia. Make up the volume of the solution to ten times the amount by adding distilled water. The reducing solution used is the formaldehyde of commerce. The 40 per cent solution is diluted to a 1 per cent solution. The glass to be silvered is polished with chamois leather, and the bath is made up immediately before use by mixing two parts by volume of the silver solution with one of formaldehyde. The solution must be poured over the surface without stopping. After the lapse of five or ten minutes, at a temperature between 15 degrees and 19 degrees C., all the silver in the solution will be found to have been deposited on the glass in a bright layer, which is then washed in running water. It is then varnished, if the glass side is to be used; or polished, if the free surface is required for reflection. This method does not require the scrupulous care necessary with other methods.

The American Cotton Crop.

On June 1, the visible supply of cotton in this country for 1895 was 9,520,085 bales. This is 2,212,820 bales more than were indicated by the crop at this time last year. These figures indicate that the entire crop this season will be no less than 9,800,000 bales, an amount that has never, heretofore, been approached.

THE PROJECTORS OF THE ATLANTIC CABLE.

A special meeting of the New York Chamber of Commerce was recently held formally to receive the painting entitled "The Projectors of the Atlantic Cable," presented to it by fifty-two of the leading citizens of New York. Morris K. Jesup, chairman of the special committee having the matter in charge, presented the painting to the Chamber in an appropriate speech. Dr. Chauncey M. Depew delivered the oration, paying a glowing tribute to the memory and achievements of Cyrus W. Field, Moses Taylor, Marshall O. Roberts, Wilson G. Hunt, Professor S. F. B. Morse, Chandler White, and David Dudley Field.

The painting represents a meeting of the projectors of the Atlantic cable at the residence of Cyrus W. Field, in Gramercy Park. The venerable Peter Cooper is presiding. To the right stands Mr. Field, who is calling attention to a chart of Trinity Bay, pointing to Heart's Content as a safe harbor for landing the cable. David Dudley Field stands behind the president with a law book. Chandler White is handing estimates of expenses to Marshall O. Roberts, next to whom at the table is Moses Taylor. At the end of the table stands Wilson G. Hunt. Professor Morse is standing behind Mr. Roberts and by his side Daniel Huntington, the artist, sketching. The original idea of the picture was suggested by Mr. Field to Mr. Huntington shortly after the completion of the cable.

tervals; the Giantess after days and Excelsior only in years.


Geysers are only found in volcanic regions, the principal localities being Iceland, New Zealand and Yellowstone Park. They are generally thought to be

is to this fact that is due the eruptions of the geysers. Assuming a geyser tube to be filled with water and to be at an elevation where water will boil at the mouth of the tube at 100° Centigrade, under normal conditions the water at the mouth of the tube has not this

D. D. Field.

S. F. B. Morse. Daniel Huntington.

Wilson G. Hunt.



Peter Cooper.

Chandler White.

Marshall O. Roberts.

Moses Taylor. Cyrus W. Field.

THE PROJECTORS OF THE ATLANTIC CABLE.

GREAT FALLS AND GEYSERS—YELLOWSTONE NATIONAL PARK.

The accompanying illustrations are views in Yellowstone Park. Of all the remarkably beautiful localities of this country, that tract of land stands pre-eminent in the grandeur of its glacial and volcanic scenery; its lofty snow and ice capped mountains; its silvery lakes; and its turbulent rivers, cascades and falls. The park covers an area of about 200 square miles and comprises the greatest geyser region of the world, together with some of the most wildly beautiful scenery.

Foremost among the natural attractions of this place is the Grand Cañon of the Yellowstone and its Falls. At places this grand gorge is 2,000 feet deep, while the bottom of the cañon is hardly wide enough to permit the river to pass through, notwithstanding its wildly turbulent character. The falls are two in number, the upper and lower, and are about one-quarter of a mile apart, the first being 140 feet in height, and formed by a perpendicular cliff over which the water dashes in a smooth, silvery sheet. Below the falls the speed increases as the cañon narrows, and the river breaks into a grand roaring stream of foam and spray, only calming the instant it takes its second leap over a precipice 390 feet in height and forming the second fall. The first portion of the illustration is a view of the cañon and its upper fall.

If the Yellowstone, its cañon and its falls, can be surpassed in point of beauty and interest, the geysers and other volcanic features of the park present perhaps still more striking objects, for here are found the most beautiful geysers of the world. Some hourly shoot vast streams of steam and water high into the air, and others make themselves known only at periods of months or years. The principal and most regular geyser of Yellowstone Park is Old Faithful, which may be seen in eruption hourly, while the larger geysers erupt at greater in-

tervals; the Giantess after days and Excelsior only in years. Geysers are only found in volcanic regions, the principal localities being Iceland, New Zealand and Yellowstone Park. They are generally thought to be passages in the earth communicating with subterranean caverns or reservoirs of hot water, the periodical discharges of steam and water being due to convulsions occasioned by the generation of steam in the passages or tubes. It is known that water will boil at different degrees of heat at different elevations, and it

the sides of the mountains, presenting a most beautiful appearance in the blending of the many colors of the coral-like formations at the terraces, and in the exquisite clearness of the water. Principal among the terraces is the Minerva Terrace, which is composed of a series of successively elevated reservoirs, from one to the other of which the water flows in beautifully clear and smooth sheets. This terrace is shown in the illustration.


The Organ of the American Liner St. Louis.

The SCIENTIFIC AMERICAN, in its issue of June 15, presented an illustration of the saloon of the new American Line steamer St. Louis, showing at the further end the organ built for the vessel by Messrs. Jardine & Son, of this city. The organ is the first ever put into a sea-going vessel, and some interesting modifications in construction were necessary to adapt it to the peculiar conditions to which it is subjected. Each pipe is supported separately by fastenings which admit of expansion and contraction. All the metal fittings are of brass, instead of iron or steel, that the dampness may not affect them injuriously, and, for the same reason, no glue is used in the woodwork, but everything is screwed fast.

The entire action of keys and stops is electric, and the keyboard is forty feet away from the pipes. The contacts are frictional and, therefore, self-cleaning. The magnets controlling the pipe valves consume only 0.05 of an ampere in current, and but 2 volts tension is required. The current is supplied by a 300 ampere-hour storage battery, charged when necessary from one of the ship's lighting dynamos.

Another organ, similar to that of the St. Louis, is now being built for her sister ship, the St. Paul.

ELECTRIC cars have been prohibited on the road from Berlin to Charlottenburg. They would have passed by the Imperial Technical Institute, and experiments showed that the current for the railroad strongly affected all the apparatus in the building, so as to make delicate scientific observations and experiments impossible.



GREAT FALLS AND GEYSERS—YELLOWSTONE NATIONAL PARK.

THE OPENING OF THE HARLEM CANAL.

The improved waterway through the northerly part of this city, joining the North and East Rivers, was thrown open for navigation on Monday, June 17, 1895, with elaborate ceremonies, including a land and marine parade by civic and federal dignitaries. The ceremonies concluded with a banquet and fireworks. The term "ship canal" is really a misnomer as applied to the Harlem Canal. The canal is designed only for canal boats and small inland water craft. The Harlem River, before the canal was begun, narrowed to little more than a creek at Kingsbridge and there connected with the waters of Spuyten Duyvil Creek and then with the waters of the Hudson; this allowed a depth of only two feet of water.

The work has been carried on by the federal authorities under the direction of Geo. L. Gillespie, Lieut.-Col. of the Corps of Engineers, U. S. A., who was appointed chief engineer of the operations. It was provided that the sum of \$2,700,000 should be expended to make a navigable waterway. \$900,000 of this sum has already been spent. The channel is ultimately to be 350 feet wide and 18 feet deep. It is now only 150 feet wide. Several years will elapse before the work is completed. The present minimum depth of water in the river is nine feet.

At present the Harlem River is practically limited for navigation to the point marked by High Bridge. When dredged out and completed to the Hudson River a clear waterway will be provided for all vessels able to pass through the draw and under the High Bridge. In transit from the North River to the Sound this route will cut off a distance of 10 or 12 miles.

We have heretofore illustrated this great engineering work, and full details thereof are reproduced in our SUPPLEMENT, No. 1015.

Testing the Great Lens.

A test of the 40 inch lens for the great Yerkes telescope took place a few days ago at the establishment of Alvan G. Clark, at Cambridge, Mass. The observatory of the Chicago University was represented by Prof. T. J. See. The test was made with Arcturus, Saturn, and double stars. The astronomers present were much pleased with the lens, which will soon be ready for delivery. According to the Boston Evening Transcript, a most novel form of telescope, which was highly praised by the company gathered at Mr. Clark's shop, was the binocular telescope constructed for D. W. Edgecombe, of Newington, Conn. This may be popularly described as a huge opera glass. It consists of twin telescopes of 6¼ inches aperture, which lie side by side precisely as do the tubes of the opera glass.

A Milk and Cream Separator Bursts with Fatal Results.


At Pittsburg, Pa., on June 18, by the explosion of a milk and cream separator, revolving at the rate of 13,000 times a minute, an accident occurred at 2110 Carson Street, south side, resulting in the death of Philip Deihl, vice-president of the Milk Dealers' Exchange of Western Pennsylvania, and the serious but not fatal injury of James R. Miller, Otto Winterhalter, and Albert Winterhalter, milk dealers. It required 8,500 revolutions per minute for the machine to separate the cream from the milk. A greater number of revolutions is dangerous. In some manner the separator did not perform its work, and the revolutions increased suddenly to 13,000, when it exploded.

Of the English Bench of Bishops twelve are pledged abstainers.

The Bicycle.

The value of the bicycle as an aid to health has been dwelt upon since the beginning of the sport, but there are other advantages to be derived from it of equal or greater importance.

Cycling cultivates the habit of rapid thinking—indeed, one whose mind is not more than ordinarily alert, and whose muscles cannot be trained to be the instant servants of the will, is not liable to pass through the several stages of cycling without accidents. Keen perception and good judgment are two qualities, above



OPENING OF THE HARLEM CANAL—VIEW FROM THE HUDSON RIVER.

all others, which the rider of the wheel should strive to acquire, and they are cultivated in a high degree by the "king of sports." Not only must the urban cyclist thread his way among many vehicles, electric cars, and numberless other impedimenta, but his rural brother as well has need of a cool brain, sharp eyes, and steady nerves in order to avoid the ever possible mishap. The rider should invariably be cautious, yet ready to make a bold dash to escape danger or to avoid giving annoyance to others a wheel or a foot. But still more important is the cultivation of accurate observation and of the sense of beauty developed by the proper use of the wheel. Since the cycle became the vehicle of the masses, thousands to whom their rural surroundings were practically terra incognita are turning their steeds away from city life and by a study of flowers, trees, rocks, and other natural objects are broadened in mind while strengthened in body by the vigorous exercise. To him who travels aright, landscapes be-


the scenes resembling rather those observable a century or two back than what one would associate with the present times.

On the arrival of the prisoners at the Iles de Salut they are taken to the "Camp," a clearing occupied by strongly-built iron-barred huts, furnished with double rows of hammocks. But at night the fetid atmosphere within, combined with the noisome vapors of the outer air and the ever-present swarms of stinging insects, render any but the sleep of exhaustion impossible. From the moment of his arrival the convict has no name. He is known only by the number of his hammock. The new arrivals are put to the most severe tasks—draining marshes and clearing ground—"to break their spirits." They are conducted to their work by armed guards, who are ordered to fire at the least attempt at flight. Hardly any try to escape, for they know that if they evade the bullets of the guards and their pursuit, it will be necessary to traverse the

sea and the virgin forest. At every step will lie in wait for them death by hunger, by fatigue, by disease, or by the poisoned arrows of the natives, who receive a reward for every convict they bring back, dead or alive. Meanwhile, with bodies broken by their awful toil in a climate where a walk of a hundred yards is a formidable task, they labor in the blazing sun with spades and picks. About their heads hang clouds of stinging insects. Great red ants cover their bare legs, and sometimes poisonous serpents twist about their ankles and inflict mortal wounds. They stand in trenches up to their knees in water and mire, and the exhalations rising from the earth consume them with fever, or set their teeth chattering as with cold, while the sweat rolls from their foreheads. Occasionally, in their despair, some

of the convicts revolt, in the hope, which is seldom disappointed, of finding in the bullets of their custodians a relief from this living torture. Others again go mad, or end their lives by deliberately exposing themselves to the sun, while very few ever succeed in escaping. Indeed, only once have any fugitives reached civilized countries again, and even then their period of freedom was comparatively brief.—Public Opinion.

WOMEN are not permitted to be photographed in China.



OPENING OF THE HARLEM CANAL—THE KINGSBRIDGE DRAW.

come a delight and he grows to love Nature in her varied moods. He learns, too, much of the country around him—its people and their pursuits—not only in his immediate neighborhood, but within a radius proportioned to his leisure.

As a teacher of practical geographical knowledge the wheel is the most thorough in the world; nothing approaches it in the encouragement of the love of outdoor life and appreciation of the beauties of nature, which are so apt to be lost sight of in a world almost canopied by commercial life.—Bicycling World.

The Faults of the Plow.

The primitive Egyptian and Assyrian plow consisted of a forked branch of a tree, one arm of which served as a share, loosening the soil, the other as a beam, drawn by human or by animal power. This was the original double mouldboard or lister plow, throwing the soil both ways. An improvement was made by so shaping the wooden mouldboard as to form a twisted wedge, which elevated, inverted, and carried the soil to one side only of the plow. A further improvement was made by making the point of the share of iron. Simple as it seems, it was not until April, 1831, that center draught was given to the plow by Meares, who inclined the beam inward. In 1797, Newbold patented a cast iron plow, and commenced its manufacture, but abandoned it, for the farmers said the iron plow poisoned the land. The steel and wrought iron plow was not invented until 1808. In 1788, Thomas Jefferson improved the plow by showing its proper principles of construction, and in 1836 and 1837 Daniel Webster experimented in plow manufacture, and said that none of his successes in public life had given him so much pleasure as seeing the improved plow of his own construction, drawn by six yoke of oxen of his own raising, cut broad and deep furrows through brush and saplings. In 1845, Governor Holbrook invented a method of shaping plow mouldboards symmetrically, either convex or concave.

All of the improvements which have been made in the plow, from the earliest agriculture until now, are simply modifications of the original idea: a wedge drawn through the soil, pulverizing and displacing it. No better method has been found.

The faults of the plow are serious ones. The bicycle may be credited with having brought ball bearings into general notice and showing the striking decrease of friction when sliding friction is converted into rolling friction. All of the wearing surfaces of the plow are sliding frictional surfaces, and the loss of power occasioned by friction of sticky earth upon the plows of this broad domain of ours is past computation. The plows of the day are rigid and inadjustable in form. In sandy or in loose and light soils, and in lumpy or clayey soils, in shallow or in deep plowing, in plowing at slow or at fast speed, no adjustment or change of form can be made to suit the special conditions of the work, yet these different conditions are often found in one plantation, and the plow should be capable of being modified to suit these conditions.

If a perpendicular line is drawn from the point of attachment of the harness tug and hame to the ground, and another line from the same point to the center of work in the mouldboard of the plow, and a horizontal line connecting the center of work with the perpendicular line, then the hypotenuse of the triangle thus formed represents the total tractive effort, the horizontal line, or base of the triangle, represents the useful tractive effect, and the perpendicular line represents the part of the traction which is expended in pulling the horse down upon the ground. In some cases one-third of the tractive effort of the horse is expended in increasing the pressure of the horses' feet upon the ground instead of in advancing the plow.

In a 14 inch plow the earth is elevated say 14 inches, carried sideways 14 inches and deposited, inverted, in the preceding furrow. It is easy to see that each inch of unnecessary elevation represents a great amount of unnecessary labor during the lifetime of a plow, and that the carrying of all the surface soil sideways to the preceding furrow represents a great aggregate travel of soil; that is, effort in plowing large fields.

The share of the plow, like the fluke of a ship's anchor, is shaped so as to draw down into the soil. The line of traction, from the center of the mouldboard to the center of the horse collar, tends to draw the plow out of the ground. The plow advances horizontally as a sort of compromise between these divergent lines, and there clearly results a loss of power occasioned by the line draught being in one plane while the line of traction is in another plane.

When the total weight of all the surface soil which is elevated, and also carried sideways, in plowing all the cultivated area of this country is calculated, it is clearly seen that the agriculturists of the country waste each year, in incidental but not in useful work, in excessive sliding friction, in indirect lines of traction, in unnecessary resistances caused by imperfect forms, and by inadjustability of form of the plow, a greater amount of labor than was wasted by the builder of the great Pyramid in Egypt, or in the building of the Chinese Wall. If all the soil thus removed were transported to the aggregate distance which it is transported and elevated to the aggregate height which it is elevated, in one heap, no one would dare to attempt the removal of the heap with no better implement than the plow.

Although 10,122 patents have been granted on the plow, in this country alone, it still offers a promising field for future inventors. The killing strain on the muscles of horses in starting street cars was not fully considered until the electric motor took the place of horses in street car work; then it was found that it required three times as powerful a motor to start a car as to run

it after it was started. The loss of power in vehicles by sliding friction was not understood until the bicycle, propelled by human muscle, showed the utility of converting sliding into rolling friction by ball bearings, and the labor wasted in dragging the plow will never, perhaps, be rightly considered unless inventors themselves drag the plow, and inquire into the reasons and causes of the excessive effort required by this ancient and indispensable implement upon which all civilization depends. The horse and the mule cannot complain, and so the plow remains the plow, improved in material and in workmanship, but retaining many of the faults of the plow of our remote ancestors.

It would seem that agriculturists have to observe the working of the implements they use, to notice errors of construction, to study the conditions, and should have ability to suggest means of improvement. Singularly, very few cases are known where agriculturists have invented or improved their implements. More singularly, very few radical inventions or new departures have been made by men in their own lines of work. The machinist instinctively judges a suggested improvement in mechanics by what he has seen. The lawyer naturally tests innovations by past decisions. The physician unavoidably refers to his reading or practice for approval or condemnation of anything new in his line. The agriculturist can but seldom divest himself of preconceived notions. Morse, the inventor of the telegraph, was not an electrician; Watts, the inventor of the steam engine, was not a machinist. The list may be extended indefinitely. To make a new departure, a radical invention, seems to require an ingenious man, untrammelled, open to new ideas and approaching a subject from a new side. Ask an agriculturist how a plow may be improved, and instinctively his mind will picture a crooked thing of steel and wood, which is essentially what he has seen. There are few of us who are not mentally hide-bound, fewer still who do not travel in mental ruts. There are very few who do not inherit religions, or absorb politics from newspapers, or form associates or their ideas from those they admire, or their mechanical opinions from what they have seen, or read, or heard of.

The inventor who will furnish a superior substitute for the plow will probably not be a plowman. He will almost surely be poor, for rich men cannot invent. When an inventor becomes rich, which happens but rarely, his attempts at further invention are passing queer. He will meet opposition. Others will develop his invention and reap the reward, and long after he is dead a statue will be raised to his memory, and his name will appear in the list of benefactors of the race, though but few of the millions benefited by his work will know of him or his work, or will care to know.

If the statesmen of the present time, trained as they are in the acute political methods of the times, should imitate Jefferson and Webster, their illustrious predecessors, their names might go down to distant posterity in the list of those benefactors of the world—the "Improvers of the Plow."—La. Planter.

The Care Required in Loading an Ocean Liner.

To watch the loading of grain either from an elevator or lighter into one of the mammoth vessels engaged in its transportation, is to witness one of the chief operations in the movements of the world's commerce, says a writer in Donahoe's Magazine. It is carried in long pipes, with a funnel-shaped, movable appendage at the end, which is shifted by means of a rope from one part of the hold to another, according as the stream of grain fills up the spaces. It rushes into the vessel with the velocity of a torrent, and sends a dense volume of dust and chaff upward, obscuring the depths beneath, and making the men attending the stowage below look like ghosts in the rising mist.

The "trimming" of the grain in the holds is an important part of its storage. After several thousand bushels have streamed into the hold, a dozen or more men are delegated to shovel the downpouring column in between the vessel's beams, a job for which they are paid at the rate of one cent a minute. In vessels of the Cunard stripe, it takes between twelve thousand and fifteen thousand bushels to fill a hold, and these vessels average 50,000 bushels in the total cargo. Ships carrying grain alone can take as high as 125,000 bushels, and when it is considered that from 4,000 to 7,000 bushels can be stored in an hour, every forty bushels weighing a ton, an idea can be had of the force of the torrent directed into the vessel.

Large vessels have four or five holds, and a distinction is made in storing the cargo in them. Grain, from its compact and dead weight, is reserved mostly for the center of the vessel, while cured provisions are packed as far forward and as far aft as possible, for their better preservation from the heat of the ship's fires. In some vessels, like the great Cunarders, which carry passengers as well as freight, the heaviest weight is stored in the lowest hold; this is to steady the vessel, and is called in the technical parlance of the stevedore "stiffening" the ship. It takes about 1,500 tons to "stiffen" a great Cunarder, and when this is done the lower hold is fastened and battened down, and work is begun on the next.

Insects and Flowers.

No side of natural history is more curious than the relation between insects and the flowering of plants. In the primitive and simpler plants that live in the sea the male cells are discharged into the water and row themselves along by the screwing motion of minute bristles until they reach and fertilize the egg cells of the female. In many land plants the male cells, discharged as clouds of golden pollen, are blown about by the wind; myriads perish, but a few reach their goal, and, fertilizing the young egg cells, cause them to ripen into seeds. In many cases, however, Nature has curbed so reckless a prodigality, and the colors and scents of flowers are fruits of her parsimony. It may be laid down as a universal truth, to which the exceptions are only apparent, that plants bearing brightly colored or perfumed flowers require the aid of insects to fertilize them. The colors serve to attract the attention of insects; the scents, especially in flowers that blossom by night, serve the same purpose. The insects come for the store of honey, or for the pollen of the plants, and their return gift to the plants is that, flitting from blossom to blossom, they unconsciously carry the golden fertilizing grains from plant to plant.

For most flowering plants the visits of insects are a necessity. Let one but grow some common plant, like geranium or mignonette, under glass and muslin, so that no stray insect may reach them; the flowers will be formed, the perfume will be as sweet as usual, but the blossoms will fade without forming seeds. Many of our English flowers are capable of being fertilized only by one kind of insect. Thus, to choose a familiar instance, the common red clover is visited by the humble bee; the petals are fused together, forming a narrow tube surrounding the honey glands and the organs that form the pollen. The long proboscis of the humble bee is able to reach the deeply hidden stores; but the hive bee, whose tongue is shorter, though bidden to the feast by attractive color and smell, is perforce an inactive spectator. When clover was first grown in Australia it never seeded, and it was found that the tongues of the native bees were too short to reach the pollen. Still more often the gorgeous blossoms of the tropics remain sterile in England in the absence of the particular moth or fly to which they are adapted.

Sometimes, as Darwin showed in his fascinating volume on "The Fertilization of the Orchids," the devices to secure that an insect shall not visit a flower without coming in contact with the pollen are extraordinarily complicated. An insect alights on a gaudy and sweet smelling blossom. An inviting landing place is ready in the form of a conveniently placed floral leaf; but the thing is a trick. No sooner is the platform touched than it gives way with a jerk, precipitating the hapless insect into a well of fluid. His wings are wetted, and he has to crawl out slowly. But pointed bristles prevent exit except by a narrow funnel, and, as he squeezes through that, his back becomes dusted with the sticky pollen. In most plants, however, the lures are simpler, and are adapted to many different kinds of insects. In spring, when the fields are bare, the blues and whites of the early flowers are sufficient to attract the notice of the few insects on the wing. During summer, when the world is covered with green, more glaring contrasts come into play, and the bold masses of orange and gold, of crimson and pink, appear. It is curious, however, that scarlet, the most clamant of colors, is the rarest in Europe. In the tropics and in South America it is one of the most common, and it were worth inquiring if European insects be color blind to scarlet. At night, when crimson and blue, pink and orange, become invisible, pale yellows and luminous whites attract the night-flying insect by their phosphorescent radiance.

The scents of plants are almost more potent lures than their colors. At night they are naturally more varied and more potent. To drift in a backwater in a summer night, or to loiter in a wood, is to set one dreaming of the spices of the tropic isles. The scents of the day are shy and indistinct; only in the mass one notices them, as in passing through a bean field, or by a thicket of gorse. But at night each blossom that is not asleep sends out a clamorous and insistent odor, and at the same moment one notices a dozen distinct and striking perfumes. But, by day or by night, the scents are not all such as are pleasant to us. Some indeed are not even within our consciousness. Thus the flowers of the Virginian creeper are almost invisible; they have green corollas and are hidden under the foliage. To us they have no scent, yet bees come to them from great distances, and during their season they are always crowded with visitors. Some of the scents most dear to us are despised by many insects. Butterflies will pass honeysuckle itself, or, indeed, any flowers with a honeysuckle scent, unnoticed. At night, however, large hawk moths, by their attention to honeysuckle, show that they share our ideas of what is pleasant. Butterflies and bees, like ourselves, are unattracted by the carrion-like smell of many plants, but these latter are visited by many beetles and flies, to which the perfumes of the rose and the violet are unattractive.—London Saturday Review.

RECENTLY PATENTED INVENTIONS.

Railway Appliances.

LIFTING JACK AND TRACK LINER.—Thomas McManus and George K. Smart, Atchison, Kansas. For conveniently and rapidly raising and shifting the rails and ties without injury to the track bed or track, these inventors provide a device consisting principally of a horizontal base or lining bar on which slides a hollow post or bar with or without roller bearings, a lifting bar adapted to support the rail sliding in the post. On the inside of the lifting bar, which carries a foot to support the base of the rail, are ratchet teeth engaged by a pawl having its pivot end in a recess in the lifting ram, which slides vertically in the lifting bar. For heavy tracks two jacks and track liners are preferably employed, the jacks being connected by a chain.

Electrical.

PUSH BUTTON.—Edwin A. Clark, Cleveland, Ohio. This button is made with a ferrule having an inwardly turned flange in which is a plug of insulating material carrying two contact points, a metallic cap with flaring sides having movement within the ferrule inside the flange, and being adapted to touch the contact and points, but being normally held away therefrom by a coiled spring resting on the insulating plug and pressing the cap outwardly. The device is very simple and inexpensive.

Mechanical.

PULLEY BLOCK.—Oliver Spitzer, Brooklyn, N. Y. To enable the operator to instantly lock the pulley or sheave, with the load suspended, or release the pulley when it is desired to hoist or lower the load, is the object of this invention. A star wheel on the pulley shaft is adapted for engagement by a pawl on one end of which is a shoulder against which a spring-pressed lever is adapted to abut, the lever being under the control of the operator, while a catch, also under the control of the operator, is adapted to engage the lever when its end is swung out of contact with the shoulder of the pawl. The device may be readily applied to any pulley block.

HAMMER.—Clarence McC. Eveleth, Plymouth, N. H. This is an improvement in hammers which have a claw for drawing nails, and provides a tool by which the nails may be drawn without marring the work and without bending the nails. A spring-pressed plunger, having a cushioned outer head, slides within a socket of the hammer head and a longitudinal recess in the handle, the plunger having notches or ratchet teeth on one side adapted for engagement by a spring latch when the plunger is withdrawn within the handle, or when it is in extended position, with its cushioned head bearing against the work.

BRICK OR TILE CUTTING MACHINE.—James C. Steele, Statesville, N. C. In this machine a cutter is movable transversely through the clay bar as it is fed out of the bar-forming mechanism, a support for the cutter being movable in the arc of a circle transversely to the clay bar, and there being mechanism for continuously reciprocating the support laterally and for oscillating the cutter at the necessary intervals. The machine is automatic in its operation, and the several parts are readily adjustable to cut the clay bar into different lengths.

SLATE DRESSING AND SIZING MACHINE.—Humphrey F. Morgan, Delta, Pa. In this machine a bed frame is movable vertically in guideways in a main frame, a toggle frame with which is connected a windlass shaft and lever supporting the bed frame. A carriage is movable on the bed frame, and independent weights are connected with and arranged to operate the carriage in reverse directions. The carriage is wide enough to permit several plates to be rested side by side thereon, and it is drawn under the polishing wheel as fast as the latter cuts its way on the surface of the slate, slates being ground or polished at each movement of the carriage back and forth.

CONTINUOUS CIGARETTE MACHINE.—Edward R. Colgin, Richmond, Va. This is a machine of simple and compact construction to which the loose tobacco is fed on endless aprons, and in which the filler rod-forming devices and the wrapping, and the pasting and cutting mechanism, are so arranged and connected as to positively and uniformly operate to form the cigarettes and cut them without reducing or marring the filler at the ends. There are also depositing and receiving devices whereby the cigarettes as they come from the machine are packed without any jar to cause the tobacco to crumble and drop out, making a bad-looking, unsalable article.

Agricultural.

PLOW.—William H. Mitchell, Glasgow, Ky. This is a combined right and left hand plow, the right and left hand point being carried by the same mould board upon a single standard, and one land side being used in connection with both points. The plow is capable of use on hill sides as well as upon level land, and is a right hand one going in one direction and a left hand one when traveling in the opposite direction, the change being brought about quickly by a reversal of the beam. Means are provided whereby the beam may be readily reversed upon the standard and held in any position necessary by a simple locking device.

GRAIN SEPARATOR.—Erastus E. Mendenhall, Thomasville, N. C. This is a machine especially adapted for separating wild onions, etc., which occasionally grow among wheat, from the wheat kernels. The machine has toothed and yielding surfaced separating cylinders between which the wheat and foreign substances are fed, the hard kernels of wheat being received in the elastic or flexible surface of the cylinder, while the soft foreign matters are taken up by the teeth of the separating roller or cylinder and carried to a separate chute from that in which the wheat is discharged.

Miscellaneous.

SAVING COAL DURING COMBUSTION.—David G. Stokely, Dallas, Texas. This invention pro-

vides a cheap and practical composition of ingredients for application to the fuel in a stove to intensify combustion, prevent clinkers, aid to burn the smoke, and effect a marked saving of the coal used as fuel. The composition consists of salt, charcoal, saltpeter, carbonate of zinc and borax, mixed in certain proportions with water and sprinkled on the coal. These ingredients, vaporized by the heat, assimilate with the carbon gas thrown off from the burning coal and render it more inflammable, thus effecting a more perfect combustion.

TREE SAWING MACHINE.—Frank Costa, Carbonado, Washington. This is a machine designed to saw standing trees. It has pivoted main and side bars, each with a device to secure it to a tree, a carriage on which is journaled a saw being slidable on the side bar, and a crank shaft on the carriage being geared to the saw, while gear wheels on the feed screw and the saw mandrel mesh with a gear wheel on the operating shaft, whereby the saw and its feed mechanism are simultaneously operated. The machine is so arranged that when used on a large tree it may be conveniently made to saw a kerf first on one side and then on the other.

WINDOW CURTAIN HANGER.—Charles M. Dilger and Henry Birnbaum, Rapid City, South Dakota. The hanger frame, according to this invention, is made in sections, adjustable one on the other, and with bearings for the roller, the frame being adapted to be raised or lowered on the window frame. By manipulating the cords the hanger may be raised or lowered to raise or lower the roller and the curtain or shade, so that light and air may be admitted directly through the upper sash.

KNOTTER AND BINDER.—Walter Connor, Toledo, Ohio. This is an improvement in devices for binding bundles and tying knots in the binding twine. It comprises a machine in which is a pivoted needle and a pivoted elbow lever, and a rod pivoted to both, there being a catch or holder on one end of a shaft on which is a pinion engaged by a rack on a tilting arm, a rod being connected to the tilting arm and elbow lever. The machine is hand operated, and facilitates the automatic tying of small bundles or packages, such as bunches of flowers, etc., the twine being severed after the knot is tied and a register made of the number of bunches tied.

POT.—Robert L. Steen, Lawrence, Kansas. In this pot it is designed to prevent all escape of steam, so that none of the valuable properties of the materials under treatment will be lost by escaping with the steam. A valve is made to close the spout, and weighted arms pivoted to the spout have their upper ends pivoted to the valve, stops secured to the spout limiting the outward swinging movement of the arms.

FINGER PROTECTOR.—Emma Grimes, Norfolk, England. This is a guard for the goods holding or guiding fingers in hand sewing. It is a tapered finger of soft rubber, having an opening at the finger tip, and an annular flange surrounding it, this end opening exposing a sensitive portion of the finger tip for use in manipulating the goods.

POLISH COMPOSITION.—William J. Birkenstock, New York City. This is a compound for polishing marble and other stones, one sufficiently fine and homogeneous to give a high polish and sharp enough to cause the polishing to be rapidly done, and intended to take the place of an ordinary grit. It is a composition in which are brass, lead, shellac and emery, prepared after a designated formula, and applied in the same manner as grit.

SURGEON'S TABLE.—Lyman G. Barton, Willsborough, N. Y. This table has independently movable leaves at opposite ends for the head and feet, and means for changing the angle of the table as a whole without altering the angle of the head and foot leaves in relation to the middle section; it also has various attachments for holding the limbs of a patient, and the parts of the table are very light and strong and readily separable. The table may be readily taken apart and folded in a very small compass.

VETERINARY APPLIANCE.—Joseph H. Gunning, New York City. This is a cannula designed to facilitate the breeding of a mare or other animal, and also affords an instrument which may be applied in the treatment of a wound.

RAT TRAP.—Joseph Klar and Frank H. Hall, Anna, Ill. This is an improvement on a formerly patented invention of the same inventors, and provides safeguards or locks of a simple form to prevent the animal when entrapped from leaving the compartment of the trap into which it may have entered. The invention affords a trap of inexpensive construction, and one in which the parts operate automatically.

NOTE.—Copies of any of the above patents will be furnished by Munn & Co., for 25 cents each. Please send name of the patentee, title of invention, and date of this paper.

NEW BOOKS AND PUBLICATIONS.

THE ORIGINS OF INVENTION. A study of industry among primitive peoples. By Otis T. Mason. With illustrations. London: Walter Scott, Ltd. New York: Charles Scribner's Sons. 1895. Pp. 419. Price \$1.25.

No subject has taken a more pleasing aspect with the advance of science than has anthropology. The present charming work, based largely on the collections of the United States National Museum, cannot be too warmly commended, for the young and old alike. A deeply interesting portion of it is that devoted to the manufacture of stone implements and the tools of aboriginal workers. One interesting point brought out is that the old stone worker would throw away, after a few blows, as many as ten boulders before he could get one which would suit him. The results of Mr. Holmes' investigations are given here, with full illustrations. The work is written on the principle of studying the past as largely as possible by the light of the present, thus making what might be a dry science one of the most vivid interest. The art of war seems somewhat insufficiently treated, the chapter being very short, and, curiously enough, the boomerang is en-

tirely omitted; that is, as far as the index is concerned. On the whole, we feel that we cannot too warmly recommend the book.

HANDBOOK OF THE TURF, A TREASURY OF INFORMATION FOR HORSEMEN. Embracing a compendium of all racing and trotting rules; laws of the States in their relation to horses and racing; a glossary of scientific terms; the catch words and phrases used by great drivers, with miscellaneous information about horses, tracks, and racing. By Samuel L. Boardman. New York: Orange Judd Company. 1895. Pp. x, 303. Price \$1.

It is well to know a little of everything, so it is fair to assume that this dictionary, which is an alphabetical cyclopedia, will receive a warm welcome from all interested in horsemanship. It seems as if the title hardly does it justice, as it really ought to be called a dictionary of equestrianism. In addition to the text proper, numerous quotations are given, and much specific information is printed in smaller type.

THE BUILDING OF A NATION. The growth, present condition and resources of the United States, with a forecast of the future. By Henry Gannett. New York: The Henry T. Thomas Company. Illustrated with maps, charts, and diagrams. 1895. Pp. xx, 252. Price \$2.50.

The particular subject of this work is treated definitely from the standpoint of the statistician and census expert. There are very numerous plates conveying, by the census system of colored areas, the greatest variety of statistical information. Many maps are given of the United States, each for the purpose of indicating some specific series of data. The book really represents a small census provided with comments requisite to develop its full utility. It is based on the census of 1890 and, of course, much of its information refers to previous years as well. In order to make it an actual history, the total rural and urban population of each census is carried back to the last century, and many of the tables of data begin in 1790 and end with 1890. Eleven different censuses, therefore, are made tributary to the volume. The table of contents and index leave nothing to be desired.

"The Bachelor of Arts" is the title of a new monthly magazine devoted to university interests and general literature. John Seymour Wood is the editor and Walter Camp and Edward S. Martin are associate editors, Henry G. Chapman, of No. 15 Wall Street, New York, being the business manager. The "advisory board" exhibits a long list of distinguished names from twenty-five different colleges and universities, and contributions to its pages are expected from many eminent writers. Typographically the new magazine is quite unique in its appearance, and its form is such that it may be readily carried in the pocket.

Any of the above books may be purchased through this office. Send for new book catalogue just published. MUNN & Co., 361 Broadway, New York.

Notes & Queries

HINTS TO CORRESPONDENTS.

Names and Address must accompany all letters, or no attention will be paid thereto. This is for our information and not for publication. **References** to former articles or answers should give date of paper and page or number of question. **Inquiries** not answered in reasonable time should be repeated; correspondents will bear in mind that some answers require not a little research, and, though we endeavor to reply to all either by letter or in this department, each must take his turn. **Buyers** wishing to purchase any article not advertised in our columns will be furnished with addresses of houses manufacturing or carrying the same. **Special Written Information** on matters of personal rather than general interest cannot be expected without remuneration. **Scientific American Supplements** referred to may be had at the office. Price 10 cents each. **Books** referred to promptly supplied on receipt of price. **Minerals** sent for examination should be distinctly marked or labeled.

(6560) W. H. K. says: Please advise through Notes and Queries, SCIENTIFIC AMERICAN, how to fasten rubber rollers used on clothes wringers which have been turned loose from shafts. A. 1. Clean shaft thoroughly between the shoulders or washers, where the rubber goes on. 2. Give shaft a coat of copal varnish, between the shoulders, and let it dry. 3. Give shaft coat of varnish and wind shaft tightly as possible with 5 ply jute twine at once, while varnish is green, and let it dry for about six hours. 4. Give shaft over the twine a coat of rubber cement, and let it dry for about six hours. 5. Give shaft over the twine a second coat of rubber cement, and let it dry for about six hours. 6. Remove washer on the short end of shaft, also the cogwheel, if the shaft has cogs on both ends. 7. See that the rubber rolls are always longer than the space between the washers where the rubber goes on, as they shrink or take up a little in putting on the shaft. 8. Clean out the hole or inside of roll with benzine, using a small brush or swab. 9. Put the thimble or pointer on the end of shaft that the washer has been removed from, and give shaft over the twine and thimble another coat of cement, and stand same upright in a vise. 10. Give the inside or hole of roll a coat of cement with a small rod or stick. 11. Pull or force the roll on the shaft as quickly as possible with a jerk, then rivet the washer on with a cold chisel. 12. Let roll stand and get dry for two or three days before using same. Cement for use should be so thick that it will run freely; if it gets too thick, thin it with benzine or naphtha.

(6561) G. S. W. says: 1. Give formula for making a washing compound. A. A washing powder for the finest white linen is a powdery mixture of 90 parts effloresced soda with 10 parts of hyposulphite of

soda and 2 parts of borax. 2. I want to manufacture a stove paste polish that is odorless and dustless and has good lasting qualities. A. Plumbago, 2 lb.; water, 8 oz.; turpentine, 8 oz.; sugar, 2 oz. Knead thoroughly and keep in tin boxes. Apply with a brush. 3. A recipe for making a good silver polish. A. Silver Polishing (Putz) Pomade.—Mix thoroughly 4½ parts vaseline with a few drops of essence of mirbane (nitrobenzole). Add to this by stirring 7½ parts elutriated chalk, 1½ parts burnt hartshorn, 1½ parts pulverized ossa sepiæ (cuttle bone). The mixture should be of the consistency of butter.

(6562) A. M. says: I would request you to send me a receipt for making condensed milk. A. Condensed milk is made by boiling milk in condensing pans in which the atmospheric pressure is removed. The process is described in detail in the SCIENTIFIC AMERICAN for July 12, 1890, April 19, 1884, July 13, 1889, and in SUPPLEMENT, No. 156.

Business and Personal.

The charge for insertion under this head is One Dollar a line for each insertion: about eight words to a line. Advertisements must be received at publication office as early as Thursday morning to appear in the following week's issue.

"C. S." metal polish. Indianapolis. Samples free.

Presses & Dies. Ferracete Mach. Co., Bridgeton, N. J.

Handle & Spoke Mch. Ober Lathe Co., Chagrin Falls, O.

Wood pulp machinery. Trevor Mfg. Co., Lockport, N. Y.

Screw machines, milling machines, and drill presses. The Garvin Mach. Co., Laight and Canal Sts., New York.

The best book for electricians and beginners in electricity is "Experimental Science," by Geo. M. Hopkins. By mail, \$4; Munn & Co., publishers, 36 Broadway, N. Y.

Superintendent wanted for a phosphate mine. Must be capable of managing from 500 to 800 men. Address, stating age, qualifications, references, etc., Bradley Pulverizer Co., 92 State St., Boston, Mass. Mention Scientific American.

Send for new and complete catalogue of Scientific and other Books for sale by Munn & Co., 361 Broadway, New York. Free on application.

SCIENTIFIC AMERICAN BUILDING EDITION.

JUNE, 1895.—(No. 116.)

TABLE OF CONTENTS.

1. A cottage at Bronxwood Park, Williamsbridge, N. Y., recently erected for Dr. Geo. P. Shirmer, at a cost of about \$2,500. Perspective elevation and floor plans. A pleasing design. A. F. Leicht, Esq., architect, New York City.
2. An elegant plate in colors showing a cottage at Bronxwood Park, Williamsbridge, N. Y., recently erected at a cost of \$2,200. Perspective view and floor plans. Mr. A. F. Leicht, architect, New York City. A neat design.
3. A cottage at Flatbush, L. I., recently erected for W. K. Clarkson, Esq., at a cost of \$5,000. Perspective elevation and floor plans. Mr. Christopher Myers, architect, New York City. A picturesque design.
4. A modern cottage at Bedford Park, New York City, recently erected at a cost of \$3,000. Perspective elevation and floor plans. A picturesque design. Mr. Edgar K. Bourne, architect, New York City.
5. The Bedford Park Congregational Church. Two perspective elevations and floor and basement plans. Cost complete, \$7,000. Mr. Edgar K. Bourne, architect, New York City.
6. A Colonial cottage recently erected at New Dorp, S. I., at a cost of \$3,675, complete. Perspective elevation and floor plans. Messrs. Child & De Goll, architects, New York City. An attractive design.
7. A residence at Germantown, Pa. Two perspective elevations and floor plans. Cost complete, about \$10,500. Messrs. Child & De Goll, architects, New York City.
8. The New Theater, San Luis de Potosi, Mexico. Architect, Don Jose Noriega.
9. Design for a window decoration.
10. The residence of E. P. Sandford, Esq., at Montclair, N. J. Two perspective elevations and floor plans. An elegant design. Architect and builder, Mr. E. P. Sandford, Montclair, N. J.
11. A cottage in the English half-timbered style recently erected for F. E. Kirby, Esq., at Glen Ridge, N. J. Perspective view and floor plans. E. Rollin Tilton, designer, New York City.
12. Miscellaneous contents: The Hanging Gardens of Babylon.—Perspective drawings.—Concrete roofs.—Points of support.—Architects' estimates.—An improved hot water heater, illustrated.—A new invention for raising water, illustrated.—Improved paving.—The Bommer spring hinge, illustrated.—A mixing regulator for gas machines, illustrated.—Adjustable sliding door track and hanger, illustrated.—Woodworker's improved vise, illustrated.—African mahogany.—A new steam and hot water heater, illustrated.—Powers' improved automatic chimney top, illustrated.—Improved wood working machinery, illustrated.

The Scientific American Building Edition is issued monthly. \$2.50 a year. Single copies, 25 cents. Thirty-two large quarto pages, forming a large and splendid MAGAZINE OF ARCHITECTURE, richly adorned with elegant plates and fine engravings, illustrating the most interesting examples of Modern Architectural Construction and allied subjects.

The Fullness, Richness, Cheapness, and Convenience of this work have won for it the LARGEST CIRCULATION of any Architectural Publication in the world. Sold by all newsmen. MUNN & CO., PUBLISHERS, 361 Broadway, New York.

[See note at end of list about copies of these patents.]

INDEX OF INVENTIONS	
For which Letters Patent of the United States were Granted	
June 18, 1895,	
AND EACH BEARING THAT DATE.	
[See note at end of list about copies of these patents.]	
Adjustable chair, F. C. Price.....	541,249
Antifriction block, G. M. Mullen.....	541,251
Armature for electric motors and generators, J. F. McLaughlin.....	541,380
Bag, See Mail bag. Traveling bag.....	541,352
Balance, C. N. Fenner.....	541,434
Baling press, Livingston & Mason.....	541,370
Band cutter and feeder, R. Johnson.....	541,236
Barrel making machine, A. B. Miner.....	541,245
Bath, See Bath tub. Bath tub.....	541,271
Bath tub, etc., Clifford & Sutter.....	541,068
Battery. See Storage battery.....	
Battery cell, portable galvanic, F. A. Glasgow.....	541,850
Bean scourer and cleaner, J. Skinner.....	541,385
Bearing, antifriction, W. H. Wright.....	541,136
Bearing for vehicle wheels, ball, E. A. Jones.....	541,227
Bearing, stop, B. D. Whitney.....	541,353
Bedstead attachment, G. W. Thompson.....	541,239
Berry picking machine, A. H. & A. H. Bassett, Jr.....	541,307
Beverages, effervescent mixture for, R. Wichmann.....	541,255
Bicycle change gear, V. Belanger.....	541,260
Bicycle gear, O. F. Good.....	541,270
Bicycle pedal, H. F. Kendall.....	541,238
Bicycle rim, W. H. & C. Roehr.....	541,119
Blackboard, annunciating, J. E. Wenger.....	541,403
Bleaching process, apparatus, H. Blackman.....	541,147
Block, See Antifriction block.....	
Block for blankbooks, removable, J. D. Mets.....	541,108
Botton holder and thread catcher, T. J. Murdoch.....	541,377
Boiler. See Sectional boiler. Steam boiler.....	
Boiler cleaner, I. C. Gray.....	541,272
Boiler furnace, E. A. Wilkinson.....	541,405
Boiler, See Sectional boiler.....	
Bottle, J. E. Valentine.....	541,133
Box. See Ash box. Display box. Match box.....	
Box trimming machine, H. W. Morvan.....	541,376
Bracket. See Shelf bracket.....	
Brake. See Car brake. Pressure brake. Vehicle brake.....	
Brake shoe, M. T. A. Kubierschky.....	541,099
Bridge construction, C. H. Platt.....	541,213
Briddle bit, G. V. & A. E. Ives.....	541,279
Brush, rotary hair, E. I. Busby.....	541,065
Brush, rotary, C. Clarke.....	541,224
Buoy for floating buoys and attaching lines thereto, F. Canney.....	541,313
Buoy, life, F. Barathon, Aine.....	541,340
Burner. See Gas burner. Oil burner.....	
Bushing and stopper, bung, B. Rubenstein.....	541,122
Button backing machine, pearl, S. Nachtigal.....	541,382
Butter churn, C. H. Wilson.....	541,137
Calcium carbide, product existing in form of crystalline, T. L. Willson.....	541,138
Calculator, mechanical, C. C. Kennison.....	541,361
Camera. See Magazine camera. Roll holding camera.....	
Can. See Cooling can. Self-opening can.....	
Car brake, electric, G. B. Damon.....	541,073
Car cylinder dust guard, Amann & Thomas.....	541,144
Car coupling, J. T. Crews.....	541,315
Car coupling, V. Erbach.....	541,432
Car coupling, C. A. Tower.....	541,400, 541,401
Car coupling, automatic, L. O. Leach.....	541,323
Car draughting machine, railway, W. Stephan.....	541,329
Car fender, J. L. Canham.....	541,312
Car fender, A. Decker.....	541,268
Car fender, J. Nagele.....	541,383
Car fender, safety, G. P. Kato, Jr.....	541,282
Car protector, C. G. Ingalls.....	541,322
Car register, stop, E. B. Michaud.....	541,267
Car street, F. A. Baier.....	541,415
Cash register and indicator, J. P. Cleal.....	541,264
Chair. See Adjustable chair.....	
Chamber vessel attachment, G. M. G. Weston.....	541,219
Change handling device, G. R. Crump.....	541,267
Checkrein lock, H. Baker.....	541,268
Child's hoop, F. W. Andrus.....	541,413
Churn, Maddox & Dunlap.....	541,173
Churn power, J. T. Gilbert.....	541,437
Cigar stamping die, E. N. Cusson.....	541,226
Cigarette machine, continuous, H. Korte.....	541,364
Cigarette stamping machine, J. W. Newall.....	541,267
Clock, C. A. Jacques.....	541,207
Clothes line fastener, C. L. Feinberg.....	541,348
Clothes rack, W. A. Bode.....	541,309
Clutch, C. B. Rumsey.....	541,444
Coal washer, G. E. Giles.....	541,324
Coating head and bit, J. Kuehne.....	541,100
Coarse cooler, J. Stanton.....	541,296
Cot, extensible, J. C. Fiegel.....	541,157
Cotton compress, roller, C. L. Bessonet.....	541,418
Coupling. See Car coupling.....	
Cranberry picker, J. M. & S. B. Moody.....	541,109
Crowder, C. M. Schenck.....	541,181
Cultivator for listed corn, E. E. Hartzell.....	541,230
Cultivator tooth, E. A. Ovenshire.....	541,177
Current strength indicator, P. G. Burgess.....	541,148
Curtain fixture, C. O. Dutcher.....	541,153
Cutter. See Band cutter. Hay, straw, or fodder cutter.....	
Cyanides, making, H. V. Castner.....	541,066
Cyclometer, W. S. Bigby.....	541,452
Damper, A. S. Held.....	541,162
Dash pot, F. W. Gordon.....	541,351
Dating and numbering device, W. Murphy.....	541,247
Dental tool, C. M. Schenck.....	541,211
Die. See Sectional die.....	
Dies, apparatus for making, Hoff & Pickles.....	541,438
Digging machine, trench, G. D. Gunn.....	541,229
Display box, J. A. McDonald.....	541,111
Door, J. A. Crismore.....	541,316
Door closing mechanism, W. S. Nightingale.....	541,181
Door fastener, sliding, F. A. Winslow.....	541,139
Door, solid or veneered, F. F. Wright.....	541,450
Draught equalizer, O. & F. Zoeller.....	541,198
Draughting apparatus, garment, F. E. Buddington.....	541,311
Dredger, A. F. Carroll.....	541,223
Drill. See Grain drill.....	
Drilling apparatus, J. F. Willard.....	541,256
Drilling machine, multiple, S. Nachtigal.....	541,381
Egg poacher, M. F. Henderson.....	541,205
Electric elevator, R. Rickemeyer.....	541,200
Electric switch, C. P. Elison.....	541,227</

The above are charges per agate line—about eight words per line. This notice shows the width of the line, and is set in agate type. Engravings may head advertisements at the same rate per agate line, by measurement, as the letter press. Advertisements must be received at Publication Office as early as Thursday morning to appear in the following week's issue.



LATHES. Shapers, Planers, Drills, Machine Shop
Outfits, Foot Lathes, Tools and Supplies.
Catalogue Free. **SEBASTIAN LATHE CO.,**
120 CULBERT ST., CINCINNATI, O.

SPECIALTIES & NOVELTIES-PATENTED
ARTICLES-SMALL OR FINE MACHINERY.
SEND FOR CATALOGUE **OTTO KONIGSLOW**
49 MICHIGAN ST. CLEVELAND, O.

ICE MACHINES. Corliss Engines. Brewers' and Bottlers' Machinery. THE VILTER MFG. Co., 899 Clinton Street, Milwaukee, Wis.

STEVENS ADJUSTABLE SCRATCH GAUGE



With fine adjustment. Sent by mail.

Price—Plain Adjustment, 6 inches.....	\$1.75
MICROMETER Adjustment, 6 inches.....	2.00

Ideal and Leader Spring Dividers and Calipers, Ideal Surface Gauges, Depth Gauges, and Fine Machinists Tools.  Illustrated catalogue free to all.

J. STEVENS ARMS AND TOOL CO.,
P. O. Box 280, Chicopee Falls, Mass.

IDEAS DEVELOPED. Absolute secrecy. Send for particulars. Advice and suggestions free. Correspondence and sample orders solicited. 25 years in business. **Gardam & Son, 98 John St., New York**

BARNES Foot-Power

MACHINERY.

FOR WOOD AND METAL WORK.

Available for:

- Carpenters,
- Collard Makers,
- Machinists,

Specialties:

- Shed Builders,
- Ironworkers,
- Marine Trade,

THE BEST FOOT POWER MACHINES IN THE WORLD.

W. F. & JOHN BARNES CO., 1595 RUBY ST., ROCKFORD, ILL.



CATALOGUE
FREE.

Send for
Illustrated
Circular
and
Catalogue
Free.

BI-SULPHIDE OF CARBON for use in the arts, Killing Insects in Grain, Killing Burrowing Animals, etc. Manufactured by **E. R. TAYLOR**, Cleveland, Ohio.

AMERICAN PATENTS.—AN INTER
esting and valuable table showing the number of patent
granted for the various subjects upon which petition
have been filed from the beginning down to December
31, 1894. Contained in **SCIENTIFIC AMERICAN SUP**
PLEMENT, No. 1002. Price 10 cents. To be had at
this office and from all newsdealers.

GATES ROCK AND ORE **BREAKERS**

OVER 3000
IN USE
THROUGHOUT
THE WORLD



**GREAT CAPACITY USING LESS
POWER THAN ANY OTHER ON EARTH**


**MODERN
MINING MACHINERY**
OF EVERY DESCRIPTION

GATES IRON WORKS DEPT. T
650 ELSTON AVE. CHICAGO.

NOW READY !

Seventeenth Edition of

Experimental Science



REVISÉD AND ENLARGED.

120 Pages and 110 Superb Cuts added.

Just the thing for a holiday present for any man, woman, student, teacher, or anyone interested in science. In the new matter contained in the last edition will be found the Scientific Use of the Phonograph, the curious optical illusion known as the Anorthoscope, together with other new and interesting Optical Illusions, the Optical Projection of Opaque Objects, new experiments in Projection, Iridescent Glass, some points in Photography, including Hand Cameras, Cane Cameras, etc. Systems of Electrical Distribution, Electrical Ore Finder, Electrical Rooker, Electric Chimes, How to Color Photographs, Study of the Stars and Planets, and many other new matter which will prove of interest to scientific readers.

840 pages, 782 fine cuts, substantially and beautifully bound. Price in cloth, by mail. \$4. Half morocco, \$5.

MUNN & CO., Publishers,
Office of the **SCIENTIFIC AMERICAN,**
361 BROADWAY, NEW YORK.

INDEX.

ILLUSTRATIONS.

A

Academy of Sci., New York..... 238
Acetylene apparatus..... 203
Action, piano, frame, Bothmer..... 404
Adjuster, brake slack..... 405
Alpaca, the..... 265
Amalgamator, ore..... 36
Ampere meter, Bristol's..... 290
Animals, interesting..... 265
Ant eater, porcupine..... 265
Antelope, Koodoo..... 377
Arch, memorial, Brooklyn..... 11
Arch, triumphal, Roman..... 117
Atlanta exposition..... 105
Auto-photo-optometer..... 171

B

Banyan tree, pagoda in..... 89
Batteries, storage, charging..... 87
Battle ship Indiana..... 8
Battle ship Oregon..... 353
Berths, pneumatic..... 43
Bicycle brake, pneumatic..... 59
Bicycle exhibition, New York..... 106
Bicycle frame..... 73
Bicycle holder..... 373
Bicycle improvements..... 373
Bicycle, Keating..... 106
Bicycle, nautical..... 363
Bicycle repairing press for..... 372
Bicycle rim and tire..... 84
Bicycle saddle, wire..... 86
Bicycle, Victor..... 155
Birds of the Congo..... 169
Boat, the Layman..... 313
Boat, torpedo, the Maine's..... 376
Boats and shoes, improved..... 150
Boats, ice..... 136
Boats propelled by gasoline..... 305
Boats, torpedo, for the Maine..... 1
Boiler, improved..... 340
Boiler, water tube..... 165
Bolt cutter, new..... 249
Book copying..... 249
Bottle, wash, chemist's..... 5
Boulevard, Lafayette, New York..... 58
Bracket, crank, cycle..... 106
Brake, bicycle, Wallace's..... 59
Brake, car, improved..... 261
Brake, vehicle..... 69
Brick cutting machine..... 104
Bridge, draw, Chicago..... 296
Bridge, East River..... 113
Bridge, hose..... 362
Bridge, North Sea Canal..... 392
Bridge, Pont-y-Pridd..... 84
Bridge, suspension, proposed..... 169
Buffaloes, sporting..... 329

C

Cable, Atlantic, projectors..... 408
Cables, transportation of..... 344
Cactus dahlia..... 75
Calendar and time system..... 250
Calocalanus pavo..... 347
Camera shutter, simple..... 198
Canal drainage, Chicago..... 369
Canal, Harlem, opening..... 409
Canal, North Sea..... 392
Cannon magnets..... 73
Cannon, toy, Shimer's..... 310
Car, automobile, Serpollet..... 315
Car brake, improved..... 261
Car coupling, Dunlap's..... 212
Car coupling, Morton's..... 164
Car coupling, Sisson's..... 212
Car fender and brake..... 261
Car fender, Fees'..... 104
Car fender, revolving..... 116
Car fender, Trinchard's..... 326
Car truck, Esterley's..... 388
Card skimmer..... 385
Carriages, automobile..... 389
Carriage, electric..... 177, 213
Carriage, steam, Scottie..... 277
Cartridge tool..... 228
Ceilings, metal..... 72
Centering device..... 376
Chair, folding..... 164
Charcoal, pulverized..... 232
Check punch, new..... 262
Chimney flue cover..... 308
Chimney struck by lightning..... 132
Chuck, lathe, new..... 244
Churn, improved..... 180
City, Roman, Algeria..... 117
Clepsydra, mysterious..... 123
Clocks, Japanese..... 373
Clockwork, curiosities of..... 4
Cloud photography..... 137
College, teachers'..... 126
Color test, mechanical..... 321
Copilia vitrea..... 347
Comet, Edward Swift's..... 52
Conduit, railway, electric..... 59
Corn harvester..... 104, 164
Coupling, car, Dunlap's..... 212
Coupling, car, Sisson's..... 212
Crustacea, flying..... 347
Cultivator, sugar cane..... 36
Cutlery sharpener..... 385
Cycle exhibition, New York..... 61
Cyclometer, "Trenton"..... 405
Cyclometer, U. S..... 106

D

Dahlia, cactus..... 75
Dana, James D..... 267
Defender, yacht..... 321
Dental engine, electric..... 372
Dental tool, Philbrook's..... 133
Deseret museum..... 241
Drainage canal, Chicago..... 369
Drawbridge, Chicago..... 340
Drawer, money, Daley's..... 372
Drill press for bicycles..... 325
Drilling machine, radial..... 325

E

Earpiece, telephone..... 244
Earthenware industry..... 193
East River bridge..... 113

Eclipse of moon, photograph..... 57
Electro-artograph..... 209
Electrolysis of street pipes..... 331
Electroplating hulls..... 56
Engine, 100 horse power..... 5
Engine, dental, electric..... 372
Engine, gasoline..... 375
Engine, gasoline and boat..... 305
Engines, gas, electric light..... 341
Engine, traction, gasoline..... 294
Exhibition, cycle, New York, 66, 67..... 281
Explosion, remarkable..... 248
Exposition, Atlanta..... 165
Exposition, French (1900)..... 197

F

Fan motor, water..... 342
Faucet, Byrne's..... 324
Feedwater regulator..... 127
Fender and brake, car..... 261
Fender, car, Fees'..... 104
Fender, car, revolving..... 116
Fender, car, Trinchard's..... 326
Furnaces..... 139
Fiber machine, Green's..... 356
Finger exercising device..... 181, 324
Fire eaters..... 219
Flue expander, Patten's..... 117
Frost cracks, fossil..... 102
Furnaces, gas, American..... 24

G

Gage, boiler alarm..... 183
Garbage carbonizer..... 338
Gas engine tricycle..... 25
Gas engines, electric light..... 341
Gas furnaces, American..... 24
Gasoline engine and boat..... 311
Gasoline motor..... 375
Gasoline traction engine..... 294
Gas well, Ohio..... 216
Glass, plate, industry..... 145
Glass, window, stained..... 245
Gnu, white tailed..... 239
Grain bin, new..... 9
Gun, Gatling..... 7

H

Hame tug, new..... 388
Harvester, corn..... 104, 164
Hat, crush, straw..... 379
Heater, water, Clarke's..... 116
Heating drum, Johnson's..... 324
Herald establishment, 273, 280, 281..... 282
Hops, parasite of..... 182
Hood for carriages..... 182
Horse, evolution of..... 233
Horse power, Wood's..... 308
Horse shoe iron industry..... 41
Horse shoe, Richardson's..... 212
Hose, large angle..... 39
Hotel, Majestic..... 293
House, an attractive..... 213
House, Royal E..... 229
Hulls, electroplating..... 56

I

Ice boats..... 136
Ice formations on ships..... 184
Ice plane..... 329
Imaginations, measurement of..... 85
Indiana, battle ship..... 219
Indicator, Alpine..... 219
Indicator, level..... 148
Injector, automatic..... 171
Ink well, Black's..... 228
Iron, bar, industry..... 41
Iron, curling, Brand's..... 404

J

Jungfrau railway..... 276

K

Knitting machinery, new..... 261
Koodoo antelope..... 377

L

Lamp, safety, miner's..... 308
Lamps, incandescent, manufact..... 251
Laundries, naphtha..... 161
Laundry tubs, slate..... 152
Lead pipe manufacture..... 217
Leather staking machine..... 340
Letter copying book..... 245
Leveling device..... 325
Life line apparatus..... 52
Light, vault, Clapp's..... 87
Lightning, photograph of..... 379
Limbs, artificial..... 52
Log loader, Brough's..... 21
Lubricator, Mitchell's..... 116

M

Machine Co., National..... 337
Magnesium torch..... 218
Magnets, cannon..... 73
Meter, ampere, Bristol's..... 180
Micrograph, the..... 52
Mill, ore crushing..... 36
Money drawer, Daley's..... 340
Monument, Lick..... 153
Moon, eclipse, photograph..... 57
Mortising machine..... 187
Motor, dental, electric..... 372
Motor, fan, water..... 342
Motor, French's..... 180
Motor, gasoline..... 375
Motor, water, Rathbun's..... 236
Museum, Deseret..... 241

N

Naphtha launches..... 161
Nebula of Orion..... 74

Nitroglycerine, explosion of..... 361
North Sea Canal..... 392
North Sea Canal bridge..... 393

O

Oar lock, improved..... 182
Observatory, Yerkes..... 88
Odometer, Bell..... 405
Ore concentrator..... 36
Ore crusher..... 20
Oregon, battle ship..... 33, 353
Orion, nebula of..... 74
Oxen, sporting..... 329

P

Pagoda in banyan tree..... 89
Pampas, life in the..... 27
Parasite of hogs..... 134
Park, Yellowstone..... 408
Patent, decision relating to a..... 346
Photograph of an eclipse..... 57
Photography, cloud..... 137
Piano attachment..... 324
Pipe, lead, manufacture..... 217
Pipes, street, electrolysis..... 331
Plane, ice..... 229
Plant, water supply, DeKalb..... 401
Plat, watchmaker's..... 360
Pontifical, alumina..... 347
Pont-y-Pridd bridge..... 84
Porcelain, manufacture..... 193
Powder holder, Upton's..... 308
Power, horse, Wood's..... 308
Press, printing, Maurer's..... 356
Prunes, California..... 228
Pump, Breslau, great..... 68
Pump, force, George's..... 20
Pump gear, windmill..... 35
Pump, power, Stone's..... 308
Punch and shears, combined..... 55
Punch, check, new..... 262
Punch, plate..... 25
Purdue University..... 289, 292

R

Rail joints, welding..... 100
Railroad crossing, Elizabeth, N.J..... 65
Railway conduit, electric..... 59
Railway, elevated, Chicago..... 254
Railway station, Capistrano..... 149
Railway up the Jungfrau..... 276
Railways, suspended..... 328
Regulator, feedwater..... 149
Respirator, Loeb..... 203
Rhinceros, Sumatra..... 245
Ride, repeating, Blake..... 406

S

Saddle, wire, bicycle..... 86
Sandblast apparatus..... 277
Sash fastener..... 148
Scissors sharpener..... 69
Sharpening, cutlery..... 385
Sharpener, cutlery..... 385
Ships of war Indiana..... 8
Ship of war Oregon..... 353
Ship of war Terrible..... 353
Ships, electroplating..... 56
Ships, hulls of, electroplating..... 56
Ships of U. S. navy..... 199
Ships, war, Chinese..... 57
Ships, war, Texas and Oregon..... 32
Shutter, camera, simple..... 406
Sifter, ash, Briner's..... 249
Signaling device, electric..... 181
Skimmer, the card..... 385
Spectrum, artificial..... 308
Square and bevel..... 196
Statue of Minerva, Herald..... 273
Steamer St. Louis, saloon of..... 376
Steamer St. Paul..... 243
Street car fender..... 104
Stump puller, Wilson's..... 331
St. Louis, grand saloon of..... 376
Sugar cane cultivator..... 36
Sun spots..... 378
Sweeper, railway, Waite's..... 404
Synchronizer, electric..... 276

T

Teachers' college..... 129
Telegraph, typewriter..... 37
Telephone earpiece..... 244
Telephone system, Paris..... 97
Telephone transmitter, Blake..... 97
Terrible, ship of war..... 392
Tesla's experiments..... 185
Texas, war ship..... 32
Thimble cover, safety flue..... 308
Tiger hunting by night..... 385
Time dater, automatic..... 260
Timepiece synchronizer..... 276
Tire and rim, bicycle..... 84
Tire, elastic, Honrath's..... 324
Tool, reloading, cartridge..... 228
Torch, magnesium..... 218
Torpedo boats for the Maine..... 1
Torpedo boat, the Maine's..... 376
Torpedo plater, Seaman's..... 295
Train, steam, Bundy..... 405
Tricycle, advertising..... 120
Tricycle, gas engine..... 360
Tricycle, petroleum..... 177
Tricycle, steam..... 388
Truck, car, Esterley's..... 388
Truck, logging..... 21
Tube, speaking, electric..... 388
Typewriter, Dougherty..... 357

V

Valve, balanced..... 164
Valve gear, electric..... 133
Vander Weyde, P. H..... 197
Vault, light, Clapp's..... 52
Veneer press..... 196
Vinegar regia, the..... 361
Vinegar, white..... 181
Violin, Woollenhaupt..... 88

W

Wagon tongue support..... 212
War between Japan and China..... 105
War ships, Chinese, repairing..... 57
War ships, Texas and Oregon..... 32
Wash bottle, chemist's..... 5
Watch, bicycle and holder..... 308
Watches, curious..... 37
Water motor, Rathbun's..... 298
Water motor, Weed..... 155
Welding rail joints..... 100
Welding pump gear..... 36
Wheels, and the heart..... 279
Window glass, stained..... 345
Woodpecker, boring..... 122
Wrench, convenient..... 103
Wrench, Delhommer's..... 342

Y

Yacht Defender..... 321

MISCELLANY.

Figures preceded by a star (*) refer to illustrated articles.

A

Academy, French..... 92
Academy of Sci., Natl..... 291
Academy of Sciences, New York..... 259
Acetylene..... 118, 178
Acetylene apparatus..... 203
Acetylene as an illuminant..... 83
Acid, phosphoric, liquid..... 42
Acid, prussic, antidote for..... 82
Adjuster, brake, slack..... 405
Africa, notes on..... 227
Agricultural machines wanted..... 164
Air, compressed, water raising..... 307
Air, liquefied, dangers of..... 264
Air pressures, working..... 307
Alabaster mines..... 274
Alaska, gold regions of..... 299
Aliens may become engineers..... 225
Alkaloids of cacti..... 146
Alloy, coin..... 26
Alloys, aluminum..... 230
Alloys, rare..... 267
Alpaca..... 265
Alps, lectures on..... 25
Animals, a large..... 36
Animals, activity of..... 59
Animals, high, work in..... 230
Aluminum alloys and solder..... 230
Aluminum horse shoes..... 353
Aluminum, notes on..... 188, 259
Aluminum, uses of..... 49
Amalgamator, a large..... 436
Ampere meter, Bristol's..... 180
Amperiotry..... 263
Auaconda mines..... 23
Anesthesia in animals..... 266
Anesthetic, the first..... 116
Animals, interesting..... 265
Animals, marine, minute..... 186
Ankles, sprained, treatment..... 87
Ant eater or echidna..... 265
Ants, agricultural..... 327
Antelope, the Koodoo..... 377
Antlion for washing prints..... 323
Anthrax in human beings..... 353
Antimony in Bolivia..... 394
Antitoxin, diphtheria..... 51
Antitoxin, progress of..... 85
Apples, essence of..... 173
Apples, marketing..... 251
Arch, memorial, Brooklyn..... 11
Arch, triumphal, Roman..... 117
Ark, new element..... 132, 140, 251
Arm, plate, test of..... 229
Armor plates, American..... 8
Armor plates, new process..... 155
Armor test, remarkable..... 182
Army, head of..... 40
Arrastra, the poor man's mill..... 243
Art products, American..... 344
Arts and industries, recent..... 163
Arsenic, the word, origin..... 391
Asbestos garments..... 202
Asia and North America..... 359
Association, American..... 355
Astigmatism, what it is..... 214
Astronomy, programme, 1885..... 172
Astronomy, world's debt to..... 9
Atlanta exposition..... 105
Atmosphere, new element in..... 132
Auto-photo-optometer..... 171
Aztec ruins, Arizona..... 247

B

Bacteriology, progress of..... 55
Baldness..... 377
Balloon army service..... 71
Balloon voyage, remarkable..... 148
Balloons, captive, use of..... 153
Balloons, experiences with..... 70
Balloons, life saving..... 85
Balloons, meteorological..... 405
Banyan tree, pagoda in..... 89
Barometer and thermometer, the..... 391
Barometer, history of..... 181
Barrels, oil, old..... 282
Base line apparatus..... 179
Bass, habits of..... 38
Baths, cold, danger of..... 374
Baths, Suro..... 89
Battery, Capofarad..... 43
Battery, motor, Sandy Hook..... 248
Battery, storage, traction..... 167
Battery, thermo, new..... 346
Battery zinc, amalgamation..... 188
Batteries, storage, charging..... 87
Battle ship Indiana..... 8
Battle ship Oregon..... 333
Battle of Yalu River..... 21
Bee, hive, wax organs of..... 91
Bees, work of..... 138
Beet leaves for cattle..... 120
Beet sugar possibilities..... 354
Berths, pneumatic..... 43

C

Cable, Atlantic, projectors..... 408
Cables, transportation of..... 344
Cables, wire, preservation..... 132
Calceolary, aerial, Brighton..... 219
Cactus dahlia..... 75
Cacti, alkaloids of..... 106
Calendar and time system..... 250
California products in Berlin..... 238
Camera shutter, simple..... 198
Canal, Block Island..... 402
Canal boat, ironclad..... 196
Canal, Cape Cod..... 394
Canal celebration, Germany..... 402
Canal, drainage, Chicago..... 369, 387
Canal, improvements, important..... 8
Canal, Harlem, opening..... 409
Canal, North Sea..... 392, 394
Canal, San Blas..... 263
Canal, ship, great..... 251
Canal, ship, to lakes..... 182
Canal, lowage, electric, for..... 380
Canal, N. Y. electricity on..... 131
Canals, ship, projected..... 90
Candle, electric..... 345
Candles and soap, coloring..... 73
Cannery, floating..... 245
Cannon magnets..... 73
Cannon, toy, Shimer's..... 310
Cape Cod Canal..... 394
Car, automobile, Serpollet..... 315
Car brake, improved..... 261
Car coupling, Dunlap's..... 212
Car coupling, Morton's..... 212
Car coupling, Sisson's..... 212

Beesmer, treatment of..... 314
Bicycle, ambulance..... 362
Bicycle brake, pneumatic..... 59
Bicycle climbing, h. p. used..... 310
Bicycle exhibition, New York..... 81
Bicycle, force exerted on..... 265
Bicycle frame..... 106
Bicycle, holder..... 73
Bicycle improvements..... 373
Bicycle, invention of..... 123
Bicycle, Keating..... 106
Bicycle lamp..... 388
Bicycle, Mail, new..... 279
Bicycle repairing, press for..... 372
Bicycle, the..... 409
Bicycle, the modern..... 315
Bicycle tires, paper..... 372
Bicycle, medical..... 363
Bicycle, new use for..... 108
Bicycle, present status of..... 354
Bicycle, progress of..... 51
Bicycle riding..... 105, 137
Bicycle rim and tire..... 84
Bicycle saddle, wire..... 86
Bicycle safety, French view..... 67
Bicycle show, New York..... 66, 67
Bicycle, Victor..... 155
Bicycle, war..... 187
Bicycles in militia drill..... 182
Bicycling, healthfulness of..... 208
Bicycles and the heart..... 279
Bicyclist, female, French..... 372
Bilge keels..... 328
Bindings, old, restoration..... 391
Birds and the farmer..... 370
Birds, bower of New Guinea..... 340
Birds of the Congo..... 169
Birds, flight of..... 234
Birds, misfortunes of..... 341
Birds and their persecutors..... 89
Birds, tongues of..... 86
Bismuth in Bolivia..... 394
Blackberries, profit from..... 146
Blacksmithing, amateur..... 146
Bleaching cotton..... 359
Bleaching, electricity in..... 362
Bleaching, electrolytic process..... 323
Bleaching straw braid..... 183
Bleach hole, Klama, N. S. W..... 206
Blowpipe glass mixture..... 196
Boat, canal, ironclad..... 196
Boat, the Layman..... 313
Boat, life, jet propelled..... 98
Boat-lowering devices needed..... 351
Boat, torpedo, aluminum..... 169
Boat, torpedo, Boxer..... 376
Boat, torpedo, for the Maine..... 376
Boats, ice..... 136
Boats, pilot, steam..... 259
Boats propelled by gasoline..... 311
Boats, torpedo, for the Maine..... 1
Boats, torpedo, U. S. new..... 280
Boats, torpedo, in war..... 164
Boiler explosions..... 35, 135
Boiler, improved..... 340
Boiler, water tube, Hedger's..... 244
Boiler, injury to by grease..... 134
Boils, to arrest..... 234
Bolt cutter, new..... 165
Book, copying, Bushnell's..... 245
Books of the Aztecs..... 166
Bookmaking, evolution of..... 151
Boots and shoes, lining for..... 106
Bone black, suppression of..... 228
Bordeaux mixture..... 341, 388
Bottle, wash, chemist's..... 5
Boulevard Lafayette, New York..... 58
Boundaries, parallel..... 18
Bottle, as specimen shrub..... 108
Boxer, torpedo boat..... 376
Brains, a collection of..... 122
Brains versus luck..... 251
Brake, bicycle, Wallace's..... 59
Brake, car, improved..... 261
Brake, vehicle, Coal's..... 69
Brick-cutting machine..... 104
Brick, waterproofing..... 258
Bricks, glass..... 361
Bridge, ancient, modernizing..... 148
Bridge of concrete..... 57
Bridge, draw, Chicago..... 296
Bridge, East River..... 113
Bridge, hose..... 362
Bridge, natural, of Oregon..... 151
Bridge, North Sea Canal..... 392
Bridge, Pont-y-Pridd..... 84
Bridge, suspension, proposed..... 169
Brick, breeding of..... 329
Buffaloes, sporting..... 329
Building materials, wood fiber..... 70
Buildings, fireproof..... 9
Burner, gas, De Mare..... 330
Burner, gas, prize for..... 380
Burner, gas, incandescent..... 380
Burns, from cold..... 155
Business maxims, good..... 211
Buoy, ship's, combined..... 114

D

Dahlia, cactus..... 75
Dairy school, Wisconsin..... 250
Dana, James D..... 267
Decay, physics..... 102
Defender, yacht..... 321
Denison, A. L., the late..... 51
Dental engine, electric..... 372
Dental tool, Philbrook's..... 133
Dentistry, electricity in..... 92
Derelicts, destroying..... 188
Derelicts, destruction of..... 218
Derelicts, wanderings of..... 69
Deseret Museum..... 241, 330
Detector, submarine..... 11
Deutzia, leaves of..... 228
Device, curling..... 404
Diamond, a large..... 219
Diamonds, how proved genuine..... 371

© 1895 SCIENTIFIC AMERICAN, INC.

Davis's Brick, Tiles, and Terra-Cotta. Third Edition. Revised, Improved, and Enlarged.

JUST READY.

A Practical Treatise on the Manufacture of
Brick, Tiles and Terra-Cotta

Including Stiff Clay, Dry Clay, Hand Made, Pressed or Front, and Roadway Paving Brick, Enamelled Brick, with Glazes and Colors, Fire Brick and Blocks, Silica Brick, Carbon Brick, Glass Pots, Retorts, Architectural Terra-Cotta, Sewer Pipe, Drain Tile, Glazed and Unglazed Roofing Tile, Art Tile, Mosaics, and Imitation of Intarsia or Inlaid Surfaces. Comprising every product of Clay employed in Architecture, Engineering, and the Blast Furnace. With a Detailed Description of the Different Clays employed, the Most Modern Machinery, Tools, and Kilns used, and the Processes for Handling, Disintegrating, Tempering, and Moulding the Clay into Shape, Drying, Setting, and Burning. By Charles Thomas Davis. Third Edition. Revised and in great part rewritten. Illustrated by 261 engravings, 622 pages, 8vo. Price.....\$5.00

This volume will be sent by mail to any address in the world, or delivered by express C. O. D., freight paid, to any address in the United States for \$5.00.

A circular of 8 pages, with specimens of the illustrations, showing the full Table of Contents, will be sent free to any one furnishing his address.

HENRY CAREY BAIRD & CO.
INDUSTRIAL PUBLISHERS, BOOKSELLERS & IMPORTERS
810 Walnut St., Philadelphia, Pa., U. S. A.

MODELS & GEARS
UNION MODEL WORKS, CHICAGO

GAS ENGINE CASTINGS
also for Water Motor, Dynamo, Boiler, Engine, etc.
A. F. WEED & CO., 106 Liberty St., N. Y.

WE DON'T

want to "Bore" you but would like to Drill the fact into you that we can make you some interesting prices on Blacksmith Drills. "You will never buy cheap unless you ask the price."

Address:
Shipman Eng. Mfg. Co.
ROCHESTER, N. Y.

Auction Sale!

The Machinery formerly owned by the Portland Plush Mill Co. will be sold at auction Tuesday, July 9, at 2 o'clock P. M., at the mill in South Portland, Maine.

The machinery can be seen at the mill. Circulars furnished on application.


For further particulars apply to JOHN P. LOVELL ARMS CO., 131 Broad St., Boston, Mass.; or W. I. TWOMBLEY, 93 Exchange St., Portland, Maine.

WARREN'S NATURAL ASPHALT READY ROOFING

Durable—Easily Applied. This roofing is manufactured from natural Trinidad asphalt materials, and will not dry up and crack under exposure to the weather as coal-tar roofings do. Send for free sample of roof 12 years old, with circular and price list to WARREN CHEMICAL & MFG. CO., 85 Fulton Street, New York, U. S. A.

To Drill or File Glass as easy as you can brass, write C. V. BOUGHTON, 7th & Hudson Sts., Buffalo, N. Y.

A Valuable Book



12,500 Receipts. 708 Pages. Price \$5. Bound in Sheep, \$6. Half-Morocco, \$6.50.

This splendid work contains a careful compilation of the most useful Receipts and Replies given in the Notes and Queries of correspondents as published in the Scientific American during the past fifty years; together with many valuable and important additions.

Over Twelve Thousand selected Receipts are here collected; nearly every branch of the useful arts being represented. It is by far the most comprehensive volume of the kind ever placed before the public.

The work may be regarded as the product of the studies and practical experience of the ablest chemists and workers in all parts of the world; the information given being of the highest value, arranged and condensed in concise form convenient for ready use.

Almost every inquiry that can be thought of, relating to formulae used in the various manufacturing industries, will here be found answered.

Instructions for working many different processes in the arts are given.

Those who are engaged in any branch of industry probably will find in this book much that is of practical value in their respective callings.

Those who are in search of independent business or employment, relating to the home manufacture of sample articles, will find in it hundreds of most excellent suggestions.

Send for Descriptive Circular.

MUNN & CO., Publishers,
SCIENTIFIC AMERICAN OFFICE,
361 Broadway, New York.

Little Giant Drilling Machine WITH STRAIGHT TABLE.
Furnished also with swinging table
Arranged for both Hand and Power.
Drills from 1/4 to 1 1/2 inch hole.
Table is perfectly square with spindle and has adjustment of 16 inches.
Feed has a run of 4 inches.
Send for fully illustrated Catalogue.
WELLS BROS. & CO.,
P. O. Box B, Greenfield, Mass.

BUY
TELEPHONES

That are good—not "cheap things." The difference in cost is little. We guarantee our apparatus and guarantee our customers against loss by patent suits. Our guarantee and instruments are 100% GUARANTEED.

WESTERN TELEPHONE CONSTRUCTION CO.,
440 Monadnock Block, CHICAGO.

Largest Manufacturers of Telephones in the United States

ALCO VAPOR LAUNCH.
Engine and helm controlled from bow. Latest improved and only 12 to 1 motor now ready for the market. 18 to 40 ft. launches 2, 3, 5 and 7 h. p. No licensed engineer or pilot required. Speed and safety guaranteed. No dangerous naphtha or gasoline used.
Marine Vapor Engine Co., Jersey City, N. J.

MATCH * MACHINERY.

Latest improved. Complete plants furnished. J. S. C. DONNELLY, 1209 Buttonwood Street, Philadelphia, Pa.

COMPLETE SMALL SIZE NEW MILLING MACHINE.
Full Capacity of Large Machines. Indispensable for students, inventors, model makers, etc. For cutting gears, pinions, fluting taps and reamers and all intricate milling.
Made specially for small work. With or without tight and loose pulley countershaft.
Price within the reach of all.
Write for full particulars.
RICHARDS MFG. CO.,
Little Giant Bench Miller 218 Fulton St., Brooklyn, N. Y.

FORECLOSURE SALE.

The Works of the Gilbert Car Manufacturing Company will be sold at Auction July 2nd, 1895, at noon, at Green Island, Albany County, N. Y. Plant in good order. Apply to HALE, BULKLEY & TENNANT, Attorneys, 25 North Pearl Street, Albany, N. Y.

BRASS AND IRON GEARS. IN STOCK WITH CUT OR CAST TEETH.
SPECIAL WORK TO ORDER. SEND FOR OUR 1895 PRICE LIST.
T. F. WELCH MFG. CO., 55 SUBURBY STREET, BOSTON.

COMPOSITION AND CONSTITUTION OF Certain Alloys.—A paper by Dr. C. R. Alder Wright, F.R.S., epitomizing the author's experimental inquiries into the subject of the relations of metals to one another as regards their mutual miscibility or solubility when rendered fluid by heat. With one illustration. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, Nos. 999 and 1000. Price 10 cents each. To be had at this office and from all newdealers.

PATENTS
taken through Munn & Co. receive special notice in the Scientific American. This splendid weekly paper, elegantly illustrated, has the largest circulation of any scientific work. \$3 a year. Specimen copies free.
Address MUNN & CO.,
New York, 361 Broadway.

TYPE WHEELS, MODELS & EXPERIMENTAL WORK. SMALL MACHINERY NOVELTIES & ETC. NEW YORK STENCIL WORKS 100 NASSAU ST. N. Y.

BALL BEARING AXLES AND RUBBER TIRES.—A paper read before the Carriage Builders' National Convention, Philadelphia, October, 1894, showing the advantage to be derived from the use of ball bearings and pneumatic tires in road vehicles. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 992. Price 10 cents. To be had at this office and from all newdealers.

VANDUZEN STEAM PUMP THE BEST IN THE WORLD.
Pumps Any Kind of Liquid. Always in Order, never Clogs nor freezes. Every Pump Guaranteed.
10 SIZES.
200 to 12000 Gallons per Hour.
Cost \$7 to \$75 each. Address
THE E. W. VANDUZEN CO.,
102 to 108 E. Second St., Cincinnati, O.

VOLNEY W. MASON & CO.
FRICTION PULLEYS, CLUTCHES, AND ELEVATORS
PROVIDENCE, R. I.

ARMSTRONG'S * PIPE * THREADING
—AND—
CUTTING-OFF MACHINES
Both Hand and Power.
Sizes 1 to 6 inches.
Water, Gas, and Steam Fitters' Tools. Hinged Pipe Vises, Pipe cutters, Stocks and Dies universally acknowledged to be THE BEST. Send for catalog.
Armstrong Mfg. Co.,
Bridgeport, Conn.

Family Ice Machine Ice, etc., in a few minutes, \$10 and up. Filters, \$1.25 and up. Cookers, \$1. Seltzateurs to prepare one's self soda water, \$4.50 and up. L. DERMIGNY, 126 W. 25th St., N. Y.

Study Electricity at Home

by our correspondence method, with FREE APPARATUS. Terms low. Cat. free. Scientific Machinist, Cleveland, O.

Starrett's Universal Surface Gauge

This gauge has joint at base allowing spindle and scriber to be moved back and forth and placed in any position from upright to horizontal, to reach over, back of, and underneath.
No. 1, 9 inch.....\$2.50. No. 2, 12 inch.....\$3.00
No. 3, with two spindles, 12 and 18 inches.....\$5.00
Illustrated Catalogue Free.
The L. S. Starrett Co.,
P. O. Box 13, ATHOL, MASS.

They All Like It. The Ladies Like It. So Do The Men. Children Enjoy It.
Layman Pneumatic Boats.
See Sci. Am., May 18, 1895.
Send 4c. in stamps for our handsomely illustrated catalogue.
Address H. D. LAYMAN,
851 Broadway, New York.

NORWICH LINE
AND
The AIR LINE LIMITED
BETWEEN
New York and Boston.

ROSE POLYTECHNIC INSTITUTE,
Terre Haute, Ind. A School of Engineering, Mechanical, Electrical, Civil Engineering, Chemical courses. Well endowed. Extensive Shops and Foundry. Modernly equipped Laboratories in all departments. Expenses low. Address C. L. MEES, President.

THE FAULTLESS * QUAKER * DISH WASHER
Will make your wife smile, your daughters rejoice, your home happy and bright. You don't have to wait. It washes, rinses, dries and polishes dishes at once. No chipping or breaking, no scalding hands, you don't touch them—so simple a child can use it, lasts a lifetime. Honest agents, women or men wanted to introduce this humane device. A good paying business offered if you write at once.
The Quaker Novelty Co. Salem, O.

HAUNTED SWING. Having bought the entire interest in the Illusion Apparatus known as the Haunted Swing, patented November 7, 1893, No. 508,227; we are now prepared to sell either American or European rights. CATHCART & BARTLETT, ATLANTIC CITY, N. J.

THE "ROUND BOX" TYPEWRITER RIBBONS
M. & M. CARBON PAPERS.
Give perfect satisfaction when others fail. Used by nearly all United States Government Departments.
Samples Free upon application.
MITTAG & VOLGER,
Manufacturers for the Trade,
Cor. Park & E. E. Aves., Park Ridge, N. J.

Parson's Horological Institute.
School for Watchmakers
ENGRAVERS AND JEWELERS.
Send for Catalogue and References.
PARSON'S HOROLOGICAL INSTITUTE,
302 Bradley Avenue, PEORIA, ILL.

HELLO, CENTRAL!
Do you use telephones? If so, we can give you just what you want. Our specialty is Blake Transmitters. There is a "best" in everything, and ours are the best. We supply complete telephones or all or any of the parts to construct a telephone. Write for illustrated catalogue.
PHENIX INTERIOR TELEPHONE CO.
131 Liberty St., New York.

CALENDOLI'S TYPESETTING MACHINE.—Description of a machine recently invented by Father Calendoli, a Sicilian Dominican, which permits an experienced operator to compose fifty thousand letters an hour. With 7 illustrations. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 1005. Price 10 cents. To be had at this office and from all newdealers.

WOODEN TANKS.
For Railroads, Mills and Manufactories. Builders of Steel Towers and Tanks. La. Red Cypress Wood Tanks a specialty.
W. E. CALDWELL CO.,
217 E. Main Street, Louisville, Ky.

NICKEL AND ELECTRO-PLATING
Apparatus and Material.
THE
Hanson & Van Winkle Co.
Newark, N. J.
81 LIBERTY ST., N. Y.
35 & 37 S. CANAL ST., CHICAGO.

RECEIVER'S SALE
—OF—
WRIGHT STEAM ENGINE WORKS,
at NEWBURGH, N. Y.

As Receiver of WRIGHT STEAM ENGINE WORKS, I will sell at public auction on the 18th day of July, 1895, at eleven o'clock a. m., on the premises adjoining the City of Newburgh on the north, the real estate, machinery, tools, patents, patterns and stock on hand of the Company.

The West Shore Railroad passes through the property with a switch to the buildings. There is also a large dock on the property by which goods can be received and shipped by the Hudson River. The buildings are built of brick, except the barn, and are extensive, and contain the best of tools and machinery in excellent order. The shops are fitted with electric, steam and hand cranes. It is considered one of the best plants for manufacturing steam engines in the country.

Part of the purchase money may remain on bond and mortgage. For further particulars inquire of
JAMES K. WRIGHT, Receiver, or
A. S. & W. F. CASSEY, Attorneys,
NEWBURGH, N. Y.

ARCHITECTURE,
Mechanics, Steam Engineering, Mechanical Drawing, Electricity, R. R. and Bridge Engineering, Plumbing, Heating, Mining, English Branches. Send for free circular, stating subject wish to study or your trade. Correspondence School of Industrial Sciences, SCRANTON, PA.

THE NEWSPAPER AND THE ART
of Making It.—An address delivered at Cornell University, by Charles A. Dana, editor of the New York Sun. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 995. Price 10 cents. To be had at this office and from all newdealers.

CARBORUNDUM
HARDEST ABRASIVE KNOWN. EMERY AND DIAMOND POWDER SUBSTITUTE. IN FLOUR, POWDER, CRYSTAL, WHEEL, SLAB & HONE FORM.
CARBORUNDUM CO., MONONGAHELA CITY, PA., U. S. A.

OUR WELL DRILLS
awarded Highest Medal at the World's Fair. All latest improvements. Catalogue free.
F. C. AUSTIN MFG. CO., CHICAGO, ILL.

ARTESIAN WELLS—BY PROF. E. G. SMITH. A paper on artesian wells as a source of water supply. Essential geological conditions of artesian wells. Some chemical features of artesian well supply. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 943. Price 10 cents. To be had at this office and from all newdealers.

DEAFNESS
and HEAD NOISES relieved by using
Wilson's Common Sense Ear Drums.
New scientific invention, entirely different in construction from all other devices. Assist the deaf when all other devices fail, and where medical skill has given no relief. Safe, comfortable, and invisible; no wire or string attachment. Write for pamphlet.
WILSON EAR DRUM MANUFACTURING CO.,
Louisville Trust Co. Building, Louisville, Ky.
Mention this paper. and 1122 Broadway, New York

TELEPHONES
Transmitters, Receivers, Magneto Bells, Cords and Parts of Telephones.
Send Stamp for Catalogue.
MIANUS ELECTRIC CO.,
MIANUS, CONN.

PATENT STEEL SKELETON LEGS
ARE THE BEST.
Established 1849.
D. W. KOLBE & SON, 1339 Arch St., Philadelphia.

Telephones
Sold outright. Cannot get out of order. Guaranteed free from infringement. Suitable for exchanges or private plants. Send for Testimonials and Prices. Some good territory left for reliable agents.
MASON TELEPHONE CO., RICHMOND, VA.

EDGE TOOLS
are often nearly ruined by using a grindstone not adapted to the work. Our quarries produce a large variety of grits suitable for grinding any tool.
May we send you our Catalogue, which will give you some information?
GRAFTON STONE COMPANY,
No. 80 River Street, GRAFTON, OHIO.

USE GRINDSTONES?
If so, we can supply you. All sizes mounted and unmounted, always kept in stock. Remember, we make a specialty of selecting stones for all special purposes. Ask for catalogue.
The CLEVELAND STONE CO.
2d Floor, Wilshire, Cleveland, O.

DEAFNESS CURED! THE EAR VAPORATOR CURES DEAFNESS
ENTIRELY! Satisfactions guaranteed or money refunded. No drums. Made of gold. Circuits free.
EAR VAPORATOR CO., Y. M. C. A. Bldg., Chicago, Ill.

NAFEW-LOVELL CHECK PROTECTOR
Perfect in construction. Modern. Highly finished and Cheapest. Simple in Operation. Compact. No parts to wear out. Unlimited Guarantee. A Certain Protector. Sent on approval to any responsible firm. Price, \$3.50. Agents wanted. Catalogue sent free.
SAMUEL NAFEW COMPANY,
26 Cortlandt St., New York, U. S. A., Manufacturers.

Architectural Books

Useful, Beautiful and Cheap.

Any person about to erect a dwelling house or stable, either in the country or city, or any builder wishing to examine the latest and best plans for a church, school house, club house, or any other public building of high or low cost, should procure a complete set of the ARCHITECTS' AND BUILDERS' EDITION of the SCIENTIFIC AMERICAN.

The information these volumes contain renders the work almost indispensable to the architect and builder, and persons about to build for themselves will find the work suggestive and most useful. They contain drawings in perspective and in color, together with floor plans, costs, location of residence, etc.

Two volumes are published annually. Volumes 1 to 18, which include all the numbers of this work from commencement to December, 1894, may now be obtained at this office or from Booksellers and Newsdealers. Price, stitched in paper, \$2.00 per volume. These volumes contain all the plates, and all the other interesting matter pertaining to the work. They are of great permanent value. Forwarded to any address.

MUNN & CO., Publishers,
361 Broadway, New York.


HYPNOTISM My original method \$2. 100 pp. pamphlet 10c. One On Personal Magnetism 10c. Dr. Anderson, S. A. 6, Masonic Temple, Chicago.

Advertisements.

ORDINARY RATES.

Inside Page, each insertion. - 75 cents a line
Back Page, each insertion. - \$1.00 a line
For some classes of Advertisements, Special and Higher rates are required.

The above are charges per agate line—about eight words per line. This notice shows the width of the line, and is set in agate type. Engravings may head advertisements at the same rate per agate line, by measurement, as the letter press. Advertisements must be received at Publication Office as early as Thursday morning to appear in the following week's issue.




Keep Cool!

For Desk, Home, and Sick Room. No smell. No waste when not in use, and runs 100 HOURS before recharging battery. Thoroughly practical for near-by ventilation. KNAPP ELECTRIC & NOVELTY CO., 45 Warren St., New York

STEEL CASTINGS

From 1 to 40,000 Pounds Weight of Open Hearth, Chester or Bessemer Steel, True to Pattern. Sound. Solid. GEARING OF ALL KINDS, CRANK SHAFTS, KNUCKLES FOR CAR COUPLERS. Cross-Heads, Rockers, Piston-Heads, etc., for Locomotives. Steel Castings of every description. CHESTER STEEL CASTINGS CO. Works, Chester, Pa. Office, 409 Library St., Phila., Pa.



Kodak Quality

Some Watches sell for \$2.50. But the purchaser of a \$50.00 time-piece gets more for his money than the man with the cheap watch.


It's the Same With Cameras.

The Kodak lenses are alone worth more than some cameras which the manufacturers claim to be "as good as a Kodak." Kodaks are standard in hand camera values—because they make good pictures—because they are durable, reliable.

Handsomely Illustrated Kodak-alogue Free.

KODAKS, \$6.00 EASTMAN KODAK COMPANY.
KODETS, TO ROCHESTER, N. Y.
BULLETS, \$100.00

Premo Cameras




Premos
Produce
Perfect
Pictures

Are perfect in construction, workmanship and finish, and contain more modern improvements than any other Camera. We make several styles and guarantee them all
ROCHESTER OPTICAL CO.
22 SOUTH STREET, ROCHESTER, N. Y.

The American Bell Telephone Company,

125 Milk Street,
Boston, Mass.

This Company owns Letters-Patent No. 463,569, granted to Emile Berliner November 17, 1891, for a combined Telegraph and Telephone, covering all forms of Microphone Transmitters or contact Telephones.

A REVOLUTION!!!
A New COTTON GIN
and WOOL BURRER.

Inventive genius has at last produced a machine that will send into retirement the old Saw Gin so long tolerated, owing to enormous development in the cotton industry. The Universal Cotton Gin and Wool Burrer Company are taking out patents in the principal countries, and make claim to superiority over the system now in use on the following among other points: The new Roller Gin will preserve the fibre intact; clean the seed more thoroughly, and thus save a large amount of cotton; prevent the possibility of fire; perform the work with a minimum of power; require comparatively no repairs; require but little if any cleaning, and have no saws to sharpen. They are the acme of simplicity in construction and effectiveness in economical working. The staple delivered in the most improved condition, with the least damage to fibre ever heretofore effected. Alfred B. Shepperson, of the Cotton Exchange, New York, recognized as the most expert and authority in the cotton world, as attested by his services to the National Department of Agriculture, and the favorable reception accorded to his opinions and publications, is President of this Company; T. H. Pearce, Secretary; E. A. Kingman, Treasurer; and S. I. Johnston, Superintendent and Engineer. A hand machine and also full size power gins may be seen in operation. A limited amount of treasury stock is for sale. For full particulars address

UNIVERSAL COTTON GIN & WOOL BURRER CO.,
Room 60
FISKE BUILDING 89 STATE ST., BOSTON.

PERFORATED METAL FOR ALL USES
OF EVERY DESCRIPTION
THE HARRINGTON & KING PERFORATING CO.
CHICAGO, ILL. U.S.A. AND 284 PEARL ST. NEW YORK

ELECTRICAL Instruments, EXPERIMENTAL MACHINERY and MODELS at Reasonable Terms.
M. E. SANGER & CO., 106 Liberty Street, NEW YORK.

The KOMBI CAMERA - \$3.50

Carry in pocket. Takes 25 perfect pictures in one loading—re-loading costs 20c. Ask your dealer for it, or send for free booklet "All About the Kombi."
ALFRED O. KEMPER,
Branches: London, Berlin. 132-134 Lake Street, Chicago

F. W. G. WOOD ENGRAVER'S LINER

All sizes from No. 1 to 30, for 2 to 25 lines. Lines Uniform, Sharp and Deep. The only Liner made that will work from

black into white. Every Tool Guaranteed Perfect. Price \$1.00 each, or \$10.00 a dozen. Angle, Tint, and Lozenge tools, 75c. each. Illustrated circulars free.
F. W. G. WOOD, 41 John St., New York.
Headquarters for Jewelers' Tools and Supplies.

AGENTS WANTED FOR FINE TOOLS IN EVERY SHOP.
C. H. BESLY & CO.
CHICAGO, ILL. U.S.A.

"CHARTER" GAS AND GASOLINE Stationary Engines
1 1/2 to 35 Actual H. P.
"Sterling" Traction Engines
18 Actual H. P.
"Sterling" Portable Engines
5 to 18 Actual H. P.
CHARTER GAS ENGINE CO., P. O. Box 148, Sterling, Ill.

At 1/4 Price
Bicycles, Watches, Guns, Ruggies, Harness, Sewing Machines, Organs, Pianos, Sales, Tools, Scales of all varieties and 1000 other articles. Lists free. CHICAGO SCALE CO., Chicago, Ill.

GASOLINE ENGINES.



1 1/2 to 75 horse power. For Propelling Boats of all kinds. Cheapest Fuel, Absolute Safety, No Licensed Engineer, Simple Construction, Hundreds in Successful Use. Write for illustrated catalogue.
GLOBE GAS ENGINE CO.,
Merion Avenue & 49th Street, PHILADELPHIA, PA.

ICE-HOUSE AND COLD ROOM.—BY R. G. Hatfield. With directions for construction. Four engravings. Contained in SCIENTIFIC AMERICAN SUPPLEMENT No. 519. Price 10 cents. To be had at this office and from all newsdealers

Bristol's Patent Steel Belt Lacing.

The simplest, cheapest and most perfect Belt Fastening for all kinds of belting. Samples sent free.
The Bristol Co.,
Waterbury, Conn.

"H. B." CUTTING-OFF TOOL

We have recently purchased the patents and a stock of this cutting-off tool. The improvement over former tools is in the addition of steadying device; otherwise it will take regular blades used in Slate No. 2 Holder. SPECIAL OFFER. To reduce stock purchased and introduce the tool, we will for the present supply one of these holders complete with one 1/2 blade for \$1.50 by express or \$1.80 by mail prepaid. Send for Catalogue.
DWIGHT SLATE MACHINE CO., HARTFORD, CONN.

The New Model

Remington
No. 6
Typewriter.

MATCHLESS CONSTRUCTION, UNEQUALED DURABILITY, UNRIVALED SPEED. Many Notable Improvements.

SEND FOR ILLUSTRATED CATALOGUE.

WYCKOFF, SEAMANS & BENEDICT,
327 BROADWAY, NEW YORK.


PYROMETERS

for Indicating High Temperatures up to 3,000 degrees.

Send for Circular.
EDWARD BROWN, 309 Walnut St., Philadelphia, Pa.

King of All Roads
FIVE MODELS—LADIES' AND MEN'S.
Weights, 18 to 25 pounds.
40 Page Catalogue sent for postage.
RIDE A MONARCH AND KEEP IN FRONT
MONARCH CYCLE CO.
CHICAGO, U. S. A.
BRANCHES: New York, Memphis, Detroit, Denver, Salt Lake City, San Francisco, Portland, Toronto

THE BICYCLE: ITS INFLUENCE IN Health and Disease.—By G. M. Hammond, M.D. A valuable and interesting paper in which the subject is exhaustively treated from the following standpoints: 1. The use of the cycle by persons in health. 2. The use of the cycle by persons diseased. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 1002. Price 10 cents. To be had at this office and from all newsdealers.



\$18 buys a beautiful little Canoe; or a Magnificent Pleasure Boat for \$125
Send for 60-page illus. catalog.
J. H. RUSHTON, CANTON, N. Y.

PRIESTMAN SAFETY OIL ENGINE

"Phenomenally low in cost of operation."—Franklin Inst.
NEITHER Kerosene, NOT Gasoline
STEAM ENGINEER

Economical, Simple, Safe, Automatic. For Electric Lighting, Pumping, Milling, etc.
PRIESTMAN & COMPANY, Inc.
Front and Tasker Streets, - - Philadelphia

"OTTO" GAS AND GASOLINE ENGINES.
1/2 to 100 h. p. Can be used in cities or in country independent of gas works or gas machines.
No Boiler, No Danger, No Engineer.

OVER 45,000 SOLD.
The Otto Gas Engine Wks., Incorp'd, Philadelphia

OLDS GASOLINE ENGINES.

MOST RELIABLE. SMALL COST. GREAT MERITS.
Send for 1894 Catalogue.
P. F. OLDS & SON,
Box 218, Lansing, Mich., U.S.A.

BOSTON GEAR WORKS

FRANK BURGESS, Prop., 33 Hartford St., Boston, Mass. Any size. Style. Spur, Bevel, Spiral Worm, etc. Spring Motors a Specialty. Send for Catalogue.

JESSOP'S STEEL THE VERY BEST
FOR TOOLS, SAWS, ETC.
Wm JESSOP & SONS, 91 JOHN ST. NEW YORK

ENGINES, Boilers and Machine Tools. New and Second-hand. Send stamp for paper "Machinery & Supplies." W. P. Davis, Rochester, N. Y.

EMERY. Emery Wheels, Grinding Machines, and Grinders' Supplies. Quick process and large stock. When in a hurry, buy of THE TANTE CO., NEW YORK CITY, CINCINNATI, and STROUDSBURG, PA.

Patented Novelties Manufactured.
S. P. DENISON, 143 Center St., New York.

HOLLY STEAM ENGINEERING CO.
343-344 Butler Exchange, Providence, R. I.
SPECIALTIES: Holly Gravity Return System; saves One-Fifth of the Fuel. Holly Pressure-Reducing Valve; no spring, lever or diaphragm. Send for circular.

-- THE --
SCIENTIFIC AMERICAN

ESTABLISHED 1845.
The Most Popular Scientific Paper in the World
Only \$3.00 a Year, Including Postage.
Weekly--52 Numbers a Year.

This widely circulated and splendidly illustrated paper is published weekly. Every number contains sixteen pages of useful information and a large number of original engravings of new inventions and discoveries, representing Engineering Works, Steam Machinery, New Inventions, Novelties in Mechanics, Manufactures, Chemistry, Electricity, Telegraphy, Photography, Architecture, Agriculture, Horticulture, Natural History, etc. Complete list of Patents each week.

Terms of Subscription.—One copy of the SCIENTIFIC AMERICAN will be sent for one year—52 numbers—postage prepaid, to any subscriber in the United States, Canada, or Mexico, on receipt of Three Dollars by the publishers; six months, \$1.50; three months, \$1.00.

Clubs.—Special rates for several names, and to Postmasters. Write for particulars.

The safest way to remit is by Postal Order, Draft, or Express Money Order. Money carefully placed inside of envelopes, securely sealed, and correctly addressed, seldom goes astray, but is at the sender's risk. Address all letters and make all orders, drafts, etc., payable to MUNN & CO., 361 Broadway, New York.

Scientific American Supplement

This is a separate and distinct publication from THE SCIENTIFIC AMERICAN, but is uniform therewith in size, every number containing sixteen large pages full of engravings, many of which are taken from foreign papers and accompanied with translated descriptions. THE SCIENTIFIC AMERICAN SUPPLEMENT is published weekly, and includes a very wide range of contents. It presents the most recent papers by eminent writers in all the principal departments of Science and the Useful Arts, embracing Biology, Geology, Mineralogy, Natural History, Geography, Archaeology, Astronomy, Chemistry, Electricity, Light, Heat, Mechanical Engineering, Steam and Railway Engineering, Mining, Ship Building, Marine Engineering, Photography, Technology, Manufacturing Industries, Sanitary Engineering, Agriculture, Horticulture, Domestic Economy, Biography, Medicine, etc. A vast amount of fresh and valuable information obtainable in no other publication.

The most important Engineering Works, Mechanisms, and Manufactures at home and abroad are illustrated and described in the SUPPLEMENT.

Price for the SUPPLEMENT, for the United States, Canada, and Mexico, \$5.00 a year; or one copy of the SCIENTIFIC AMERICAN and one copy of the SUPPLEMENT, both mailed for one year to one address for \$7.00. Single copies, 10 cents. Address and remit by postal order, express money order, or check,
MUNN & CO., 361 Broadway, New York.

Building Edition.

THE SCIENTIFIC AMERICAN BUILDING EDITION is issued monthly. \$2.50 a year. Single copies, 25 cents. Thirty-two large quarto pages; forming a large and splendid Magazine of Architecture, richly adorned with elegant plates and other fine engravings; illustrating the most interesting examples of modern Architectural Construction and allied subjects.

A special feature is the presentation in each number of a variety of the latest and best plans for private residences, city and country, including those of very moderate cost as well as the more expensive. Drawings in perspective and in color are given, together with Floor Plans. Descriptions, Locations, Estimated Cost, etc.

The elegance and cheapness of this magnificent work have won for it the Largest Circulation of any Architectural publication in the world. Sold by all newsdealers. \$2.50 a year. Remit to
MUNN & CO., 361 Broadway, New York.

Export Edition

of the SCIENTIFIC AMERICAN, with which is incorporated "LA AMERICA CIENTIFICA E INDUSTRIAL," or Spanish edition of the SCIENTIFIC AMERICAN is published monthly, and is uniform in size and typography with the SCIENTIFIC AMERICAN. Every number contains about 50 pages, profusely illustrated. It is the finest scientific, industrial export paper published. It circulates throughout Cuba, the West Indies, Mexico, Central and South America, Spain and Spanish possessions—wherever the Spanish language is spoken. THE SCIENTIFIC AMERICAN EXPORT EDITION has a large guaranteed circulation in all commercial places throughout the world. \$3.00 a year, postpaid, to any part of the world. Single copies, 25 cents.

Manufacturers and others who desire to secure foreign trade may have large and handsomely displayed announcements published in this edition at a very moderate cost. Rates upon application.
MUNN & CO., Publishers.
361 Broadway, New York.

PRINTING INKS.

The SCIENTIFIC AMERICAN is printed with CHAS. F. JOHNSON & CO.'S INK, Tenth and Lombard Sts., Philadelphia, and 47 Rose St., opp. Duane, New York.